

## ScanSnap S1100 for PC and Mac

## Specifications

General technical specifications for the ScanSnap S1100:

For any further questions or queries please contact our scanner technical support team on +44 (0) 20 8573 4444

Product name		ScanSnap S1100
<b>General technical specifications</b>		
<b>Scanner Type</b>		ADF (Automatic Document Feeder), Simplex Colour scanning
<b>Output</b>		Colour/B&W/Automatic Colour and B&W detection
<b>Image Sensor</b>		CIS (Colour image sensor)
<b>Optical Resolution</b>		600 dpi x 600 dpi
<b>Scanning Speed (A4)</b>	<b>Normal mode</b>	Colour 150dpi, B&W 300dpi: 7.5 seconds per page
	<b>Better mode</b>	Colour 200dpi, B&W 400dpi: 7.5 seconds per page
	<b>Best mode</b>	Colour 300dpi, B&W 600dpi: 7.5 seconds per page
	<b>Excellent mode</b>	Colour 600dpi, B&W 1,200dpi: 35 seconds per page
<b>Scanning Range</b>		A4, A5, A6, B5, B6, Business card, Letter, Legal and Custom sizes (can set for up to 5 different paper types)/Automatically recognizes paper type by paper length. A3 scanning possible through optional carrier sheets, part number PA03660-0013
<b>Paper Weight (thickness)</b>		52.3 to 209.3g/m <sup>2</sup> (straight path) 52.3 to 80g/m <sup>2</sup> (U-turn path)
<b>Hopper Capacity</b>		1 sheet
<b>Interface</b>		USB 2.0 (USB 1.1 Compatible)
<b>Driver</b>		ScanSnap Specific Driver(1) (TWAIN/ISIS® not supported)
<b>Applications for Windows</b>		ScanSnap Manager v5.1, CardMinder™ v4.1, ScanSnap Organizer v4.1, ABBYY FineReader for ScanSnap v4.1, Evernote for Windows 3.5, Scan to Microsoft SharePoint 3.35
<b>Applications for Mac</b>		ScanSnap Manager v3.2, CardIris™ v3.6, ABBYY FineReader for ScanSnap v4.1, Evernote for Mac 1.10
<b>Compatible Operating Systems</b>		WIN 7/XP/Vista Mac OSx v10.6/10.5/10.4
<b>Power Requirement</b>		USB Bus Power 5v/0.5A (1 port)
<b>Power Consumption</b>		Scan Mode: 2.5W or less Sleep mode: less than 1W
<b>Operation Environment</b>	<b>Temperature</b>	5°C to 35°C (42°F to 95°F)
	<b>Relative humidity</b>	20 to 80% (non-condensing)
<b>Dimensions (W x D x H)</b>		273 x 47.5 x 34mm
<b>Device Weight</b>		350g
<b>Environmental Compliance</b>		ENERGY STAR® Compliant
<b>Limited Warranty</b>		1 year Limited Warranty. For full details, visit the warranties page or call +44 (0) 870 6000 922
<b>Service Options</b>		Advanced Exchange Upgrade – Advanced Exchange Upgrade Plus. For full details on all service programs, visit <a href="http://www.fel.fujitsu.com/assurance">www.fel.fujitsu.com/assurance</a>
<b>Part Number</b>		PA03610-B001 (S1100)

1 Twain or ISIS applications cannot be used directly.

## Compatible Operating Systems

Windows	Windows 7 (32-bit / 64-bit)	Win® XP 32-bit	Win® Vista
ScanSnap Manager v5.1	✓	✓	✓
ScanSnap Organizer v4.1	✓	✓	✓
CardMinder™ v4.1	✓	✓	✓
ABBYY FineReader for ScanSnap™ v4.1	✓	✓	✓
Scan to Microsoft SharePoint 3.35	✓	✓	✓
Evernote for Windows 3.5	✓	✓	✓

  

MacOS	MacOS X v10.6	MacOS X v10.5	MacOS X v10.4
ScanSnap Manager v3.2	✓	✓	✓
CardIris™ v3.6 for ScanSnap	✓	✓	✓
ABBYY FineReader for ScanSnap™ v4.1	✓	✓	✓
Evernote for Mac 1.1	✓	✓	✗

## Hardware Requirements – Windows <sup>(2)</sup>

Requirement	Specifications
CPU	Intel® Pentium® 4 1.8GHz or higher (recommended: Intel® Core™ 2 Duo 2.2GHz or higher)
Memory Capacity(1)	64bit : 2GB or more. 32bit: 512 MB or more (recommended : 1 GB or more)
Disk Capacity	Spare capacity of at least 2,100MB is necessary to install the software that is included in this chart. 2,470MB or more if using Rack2-Filer

## Hardware Requirements – MacOS <sup>(2)</sup>

Requirement	Specifications
CPU	OS X v10.6: Intel® Core™ Duo 1.83GHz or higher (recommended : Intel® Core™ 2 Duo 2.4GHz or higher) Power PC G5 1.6GHz or higher OS X v10.4, 10.5: Intel® Core™ Duo 1.83GHz or higher
Memory Capacity(1)	OS X v10.6: 1GB or more. OSX v10.5, 10.4: 512MB or higher (1GB or higher recommended)
Disk Capacity	Spare capacity of at least 5350MB is necessary to install the software that is included in this chart.

1 A memory capacity of 1GB or higher is recommended when scanning in "Excellent mode".

2 Scanning speeds may drop if recommended CPU, memory capacity and USB1.1 requirements are not met.