

Support Matrix

ETERNUS hybrid storage system ETERNUS AF all-flash array

ETERNUS DX S5 series
ETERNUS DX S4 series
ETERNUS DX S3 series
ETERNUS DX200F
ETERNUS AF S3 series
ETERNUS AF S2 series
ETERNUS AF series
ETERNUS DX60 S2/DX60
ETERNUS DX80 S2/DX80
ETERNUS DX90 S2/DX90
ETERNUS DX400 S2 series, DX400 series
ETERNUS DX8000 S2 series, DX8000 series
ETERNUS2000
ETERNUS4000
ETERNUS8000
Tintri VMstore series

Storage Management Software

ETERNUS SF Storage Cruiser 16
ETERNUS SF Storage Cruiser 15

対応装置一覧表

ETERNUS ハイブリッドストレージシステム ETERNUS AF オールフラッシュアレイ

ETERNUS DX S5 series
ETERNUS DX S4 series
ETERNUS DX S3 series
ETERNUS DX200F
ETERNUS AF S3 series
ETERNUS AF S2 series
ETERNUS AF series
ETERNUS DX60 S2/DX60
ETERNUS DX80 S2/DX80
ETERNUS DX90 S2/DX90
ETERNUS DX400 S2 series, DX400 series
ETERNUS DX8000 S2 series, DX8000 series
ETERNUS2000
ETERNUS4000
ETERNUS8000
ETERNUS TR series

ストレージ基盤ソフトウェア

ETERNUS SF Storage Cruiser 16
ETERNUS SF Storage Cruiser 15

25th Edition
Nov, 2019

FUJITSU Ltd.

Copyright FUJITSU LIMITED 2008-2019

ETERNUS SF Storage Cruiser 16

Model Name	Firmware Version	ETERNUS SF Storage Cruiser 16									
		16.0	16.1	16.2	16.3	16.4	16.5	16.6	16.7	16.8	
ETERNUS DX60 S5 ETERNUS DX100 S5 ETERNUS DX200 S5	V11L30/V11L31	N	N	N	N	N	N	N	N	Y Apply patch	
ETERNUS DX500 S5 ETERNUS DX600 S5	V11L20/V11L21	N	N	N	N	N	N	N	N	Y	
ETERNUS DX900 S5	V11L20	N	N	N	N	N	N	N	N	Y Apply patch	
ETERNUS DX60 S4 ETERNUS DX100 S4 ETERNUS DX200 S4	V10L70/V10L71	N	N	N	N	N	Y	Y	Y	Y	
	V10L80/V10L81	N	N	N	N	N	Y new functions are not supported	Y	Y	Y	
	V10L82/V10L83 V10L84/V10L85	N	N	N	N	N	Y new functions are not supported	Y Apply patch Refer to Table1	Y	Y	
	V10L86/V10L87	N	N	N	N	N	Y new functions are not supported	Y Apply patch Refer to Table1 new functions are not supported	Y Apply patch Refer to Table1	Y	
ETERNUS DX500 S4 ETERNUS DX600 S4	V10L80/V10L81	N	N	N	N	N	N	Y	Y	Y	
	V10L82/V10L83 V10L84/V10L85	N	N	N	N	N	N	Y Apply patch Refer to Table1	Y	Y	
	V10L86/V10L87	N	N	N	N	N	N	Y Apply patch Refer to Table1 new functions are not supported	Y Apply patch Refer to Table1	Y	
ETERNUS DX900 S4	V11L10	N	N	N	N	N	N	N	Y	Y	
	V11L20	N	N	N	N	N	N	N	Y new functions are not supported	Y	
ETERNUS DX60 S3	V10L25	N	N	Y *2,3,5	Y *2,3,5	Y *2,3,5	Y *2,3,5	Y *2,3,5	Y *2,3,5	Y *2,3,5	
	V10L50	N	N	Y new functions are not supported	Y Apply patch Refer to Table1	Y	Y	Y	Y	Y	
	V10L60	N	N	Y new functions are not supported	Y new functions are not supported	Y	Y	Y	Y	Y	
	V10L70	N	N	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y	Y	Y	Y	
	V10L80	N	N	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y	Y	Y	
	V10L82 V10L84	N	N	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y Apply patch Refer to Table1	Y	Y	
	V10L86	N	N	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y Apply patch Refer to Table1 new functions are not supported	Y	Y	
ETERNUS DX100 S3 ETERNUS DX200 S3 ETERNUS DX500 S3 ETERNUS DX600 S3	V10L10	Y *2,3,5	Y *2,3,5	Y *2,3,5	Y *2,3,5	Y *2,3,5	Y *2,3,5	Y *2,3,5	Y *2,3,5	Y *2,3,5	
	V10L20	Y *2,3,4,5	Y *2,3,5	Y *2,3,5	Y *2,3,5	Y *2,3,5	Y *2,3,5	Y *2,3,5	Y *2,3,5	Y *2,3,5	
	V10L30/V10L31 V10L32/V10L33	Y *2,3,4,5	Y *2,3,5	Y *2,3	Y *2,3	Y *2,3	Y *2,3	Y *2,3	Y *2,3	Y *2,3	
	V10L50 V10L51	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y Apply patch Refer to Table1	Y	Y	Y	Y	Y	
	V10L53	N	N	N	Y Apply patch Refer to Table1	Y	Y	Y	Y	Y	
	V10L60/V10L61	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y	Y	Y	Y	Y	
	V10L70/V10L71	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y	Y	Y	Y	
	V10L80/V10L81	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y	Y	Y	
	V10L82/V10L83 V10L84/V10L85	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y Apply patch Refer to Table1	Y	Y	
	V10L86/V10L87	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y Apply patch Refer to Table1 new functions are not supported	Y	Y	
ETERNUS DX8700 S3 ETERNUS DX8900 S3	V10L40	N	N	Y Apply patch Refer to Table1	Y	Y	Y	Y	Y	Y	
	V10L52	N	N	Y Apply patch (new functions are not supported) Refer to Table1	Y Apply patch Refer to Table1	Y	Y	Y	Y	Y	
	V10L60	N	N	Y new functions are not supported	Y new functions are not supported	Y	Y	Y	Y	Y	
	V10L70	N	N	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y	Y	Y	Y	
	V10L80	N	N	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y	Y	Y	
	V10L82 V10L84	N	N	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y Apply patch Refer to Table1	Y	Y	
	V10L86	N	N	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y Apply patch Refer to Table1 new functions are not supported	Y	Y	
ETERNUS DX200F	V10L17	Y *2,3,6	Y *2,3	Y *2,3	Y *2,3	Y *2,3	Y *2,3	Y *2,3	Y *2,3	Y *2,3	
	V10L30-V10L50	N	N	N	Y Apply patch Refer to Table1	Y	Y	Y	Y	Y	
	V10L60	N	N	N	Y Apply patch Refer to Table1 new functions are not supported	Y	Y	Y	Y	Y	
	V10L70	N	N	N	Y new functions are not supported	Y new functions are not supported	Y	Y	Y	Y	
	V10L80	N	N	N	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y	Y	Y	

	V10L82 V10L84	N	N	N	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y Apply patch Refer to Table1	Y	Y
	V10L86	N	N	N	Y new functions are not supported	Y new functions are not supported	Y new functions are not supported	Y Apply patch Refer to Table1 new functions are not supported	Y	Y
ETERNUS AF150 S3/AF250 S3	V11L30V11L31	N	N	N	N	N	N	N	N	Y Apply patch
ETERNUS AF650 S3	V11L20V11L21	N	N	N	N	N	N	N	N	Y
ETERNUS AF S2 series	V10L80	N	N	N	N	N	N	Y	Y	Y
	V10L82 V10L84	N	N	N	N	N	N	Y Apply patch Refer to Table1	Y	Y
	V10L86	N	N	N	N	N	N	Y Apply patch Refer to Table1 new functions are not supported	Y	Y
ETERNUS AF series	V10L60	N	N	N	N	Y	Y	Y	Y	Y
	V10L70	N	N	N	N	Y new functions are not supported	Y	Y	Y	Y
	V10L80	N	N	N	N	Y new functions are not supported	Y new functions are not supported	Y	Y	Y
	V10L82 V10L84	N	N	N	N	Y new functions are not supported	Y new functions are not supported	Y Apply patch Refer to Table1	Y	Y
	V10L86	N	N	N	N	Y new functions are not supported	Y new functions are not supported	Y Apply patch Refer to Table1 new functions are not supported	Y	Y
ETERNUS DX60 S2	V20L10-V20L16	Y	Y	Y	Y	Y	Y	Y	Y	Y
ETERNUS DX80 S2	V10L11-V10L40	Y	Y	Y	Y	Y	Y	Y	Y	Y
ETERNUS DX200 S2	V10L45-V10L47	Y	Y	Y	Y	Y	Y	Y	Y	Y
ETERNUS DX400 S2 series	V10L50-V10L60	Y	Y	Y	Y	Y	Y	Y	Y	Y
ETERNUS DX6000 S2 series	V10L23-V10L40	Y	Y	Y	Y	Y	Y	Y	Y	Y
	V10L45-V10L47	Y	Y	Y	Y	Y	Y	Y	Y	Y
	V10L50-V10L60	Y	Y	Y	Y	Y	Y	Y	Y	Y
ETERNUS DX60	V10L11-V10L72	Y	Y	Y	Y	Y	Y	Y	Y	N
ETERNUS DX80	V10L11-V10L72	Y	Y	Y	Y	Y	N	N	N	N
ETERNUS DX90	V10L21-V10L72	Y	Y	Y	Y	N	N	N	N	N
	V20L41	N	N	N	N	N	N	N	N	N
	V20L42-V20L86	Y	Y	Y	Y	N	N	N	N	N
ETERNUS DX400 series	V10L21-V10L72	Y	Y	Y	Y	N	N	N	N	N
ETERNUS DX8000 series	V20L41	N	N	N	N	N	N	N	N	N
	V20L42-V20L86	Y	Y	Y	Y	Y	Y	Y	Y	Y
ThinPro VMstore series/ETERNUS TR series	TrOS 3.2.2.1~	N	N	N	(Only Windows is supported)	(Only Windows is supported)	(Only Windows is supported)	(Only Windows is supported)	(Only Windows is supported)	(Only Windows is supported)
ETERNUS8000 model 700										
ETERNUS8000 model 800										
ETERNUS8000 model 1100										
ETERNUS4000 model 300										
ETERNUS4000 model 500										
ETERNUS8000 model 800										
ETERNUS8000 model 1200										
ETERNUS8000 model 2200										
ETERNUS4000 model 400										
ETERNUS4000 model 600										
ETERNUS2000 model 50										
ETERNUS2000 model 100										
ETERNUS2000 model 200										

*1: BS2000関連設定は未サポート
 *2: RAID-F以下の設定/表示は未サポート
 - REC回線番号
 - REC転送モード
 *3: iSCSIポートのマルチVLAN機能は未サポート
 *4: 以下の機能は未サポート
 - RAID-Fの利用
 - エコモード電源制御
 - NAS管理機能での、NASポートのポート結合
 - NAS管理機能での、NASインターフェースのVLAN ID設定
 - NAS管理機能での、DNSサーバの設定
 - NAS管理機能での、NASサーバの応答変更
 - NAS管理機能での、NASボリュームの容量拡張
 - NAS管理機能での、NASボリュームの置換/バックアップ/リストア
 - NAS管理機能での、NASボリュームのクォータ/スナップショット自動取得機能
 - NAS管理機能での、NASボリュームの容量制限機能(クォータ管理)
 *5: 以下の機能は未サポート
 - Extreme Cache Pool
 - REC経路の帯域設定
 - シンプロビジョニングボリュームまたはFTVの作成時における、ボリュームの名称に関する制約事項の解除
 - シンプロビジョニングプールおよびレプリカでの、RAID-FRの利用
 - NAS管理機能での、ファイル対策機能
 - NAS管理機能での、CIFS共有フォルダに対するセキュリティ機能強化
 - NASボリュームおよびNASシステムに対する性能管理機能
 *6: 以下の性能情報の取得機能は未サポート
 - 稼働日数
 - 温度性能情報
 - 消費電力性能情報
重要事項1
 パッチには修正が含まれているため、サポートの範囲に関わらず最新パッチの適用を推奨します。

*1:The setting related to BS2000 is unsupported.
 *2: Following setting and display of RAID is unsupported.
 - REC line number
 - REC transfer mode
 *3: Multiple VLAN of iSCSI port is unsupported.
 *4: Following functions are unsupported.
 - RAID-F
 - Eco-mode power control
 - (NAS Management Function) Port bonding of NAS ports
 - (NAS Management Function) VLAN ID settings of NAS interface
 - (NAS Management Function) Settings of DNS server
 - (NAS Management Function) Change in NAS server name
 - (NAS Management Function) Capacity expansion of NAS volume
 - (NAS Management Function) Inter-box backup/restore of NAS volumes
 - (NAS Management Function) Automatic collection function of NAS volume snapshots
 - (NAS Management Function) Capacity limit function (Quota management) of NAS volumes
 *5: Following functions are unsupported.
 - Extreme Cache Pool
 - Configuring the bandwidth of the REC path
 - Allocating a physical area of the entire volume area when creating a Thin Provisioning volume or FTV
 - Using RAID-FR in Thin Provisioning pools and Test pools
 - (NAS Management Function) Antivirus function
 - (NAS Management Function) Strengthening of the security function for CIFS shared folders
 - The performance management function for NAS volumes and NAS systems
 *6: Following functions of acquiring performance information are not supported.
 - Number of active disks
 - Temperature performance
 - Power consumption

Note
 Because bug fix is included in the patch, the application of the latest patch is recommended regardless of the presence of the support.

Table1. patch number

ETERNUS SF Storage Cruiser Version	Model Name	Firmware Version	patch number(Japan)		patch number(Other countries)	
			Scalers	Linux	Scalers	Linux
ETERNUS SF Storage Cruiser 16.2	ETERNUS DX8700 S3 ETERNUS DX8900 S3	V10L40 or later	T010928SP-04 or later T011025SP-03 or later T011240SP-01 or later T011247SP-01 or later T011373SP-01 or later	T010894WP-05 or later T010908WP-04 or later T011238WP-01 or later T011246WP-01 or later T011372WP-01 or later	T010928SP-04 or later T011025SP-03 or later T011240SP-01 or later T011247SP-01 or later T011040SP-02 or later	T010894WP-05 or later T010908WP-04 or later T011238WP-01 or later T011246WP-01 or later T011039WP-02 or later
ETERNUS SF Storage Cruiser 16.3	ETERNUS DX60 S3	V10L50	T012175SP-01 or later T012214SP-01 or later	T012177XP-01 or later T012213XP-01 or later	T012178LP-01 or later T012215LP-01 or later	T012177XP-01 or later T012208XP-01 or later T012213XP-01 or later T012215LP-01 or later T012211LP-01 or later

	ETERNUS DX100 S3 ETERNUS DX200 S3 ETERNUS DX500 S3 ETERNUS DX600 S3	V10L50 V10L51	T012179SP-01 or later T012214SP-01 or later	T012177XP-01 or later T012213XP-01 or later	T012178LP-01 or later T012215LP-01 or later	T012178SP-01 or later T012208SP-01 or later T012214SP-01 or later	T012177XP-01 or later T012208XP-01 or later T012213XP-01 or later	- RHEL5 T012178LP-01 or later T012215LP-01 or later T012210LP-01 or later - RHEL6, RHEL7 T012178LP-01 or later T012215LP-01 or later T012211LP-01 or later	
		V10L53	T012179SP-07 or later T012214SP-06 or later	T012177XP-07 or later T012213XP-06 or later	T012178LP-07 or later T012215LP-06 or later	T012178SP-07 or later T012208SP-01 or later T012214SP-06 or later	T012177XP-07 or later T012208XP-01 or later T012213XP-06 or later	- RHEL5 T012178LP-07 or later T012215LP-06 or later T012210LP-01 or later - RHEL6, RHEL7 T012178LP-01 or later T012215LP-06 or later T012211LP-01 or later	
		ETERNUS DX200F	V10L30-V10L5x	T012179SP-07 or later T012214SP-06 or later	T012177XP-07 or later T012213XP-06 or later	T012178LP-07 or later T012215LP-06 or later	T012178SP-07 or later T012208SP-01 or later T012214SP-06 or later	T012177XP-07 or later T012208XP-01 or later T012213XP-06 or later	- RHEL5 T012178LP-07 or later T012215LP-06 or later T012210LP-01 or later - RHEL6, RHEL7 T012178LP-01 or later T012215LP-06 or later T012211LP-01 or later
		ETERNUS DX6700 S3 ETERNUS DX8900 S3	V10L52	T012179SP-01 or later T012214SP-01 or later	T012177XP-01 or later T012213XP-01 or later	T012178LP-01 or later T012215LP-01 or later	T012178SP-01 or later T012208SP-01 or later T012214SP-01 or later	T012177XP-01 or later T012208XP-01 or later T012213XP-01 or later	- RHEL5 T012178LP-01 or later T012215LP-01 or later T012210LP-01 or later - RHEL6, RHEL7 T012178LP-01 or later T012215LP-01 or later T012211LP-01 or later
ETERNUS SF Storage Cruiser 16.6	ETERNUS DX60 S4/DX100 S4/DX200S4 ETERNUS DX500 S4/DX600 S4 ETERNUS DX S3 series ETERNUS AF S2	V10L82 or later V10L83 or later	T014536SP-01 or later T014364SP-02 or later	T014272XP-02 or later T014363XP-02 or later	T014537LP-01 or later T014365LP-02 or later	T014536SP-01 or later T014364SP-02 or later	T014272XP-02 or later T014363XP-02 or later	T014537LP-01 or later T014365LP-02 or later	
ETERNUS SF Storage Cruiser 16.7	ETERNUS DX60 S4/DX100 S4/DX200S4 ETERNUS DX500 S4/DX600 S4 ETERNUS AF S2 series	V10L86 or later V10L87 or later	T015136SP-01 or later	T015135XP-01 or later	T015137LP-01 or later	T015136SP-01 or later	T015135XP-01 or later	T015137LP-01 or later	

ETERNUS SF Storage Cruiser 15

Model Name	Firmware Version	ETERNUS SF Storage Cruiser 15			
		15.0B	15.1	15.2	15.3
ETERNUS DX60 S5 ETERNUS DX100 S5 ETERNUS DX200 S5 ETERNUS DX500 S5 ETERNUS DX600 S5 ETERNUS DX900 S5	All version number	N	N	N	N
ETERNUS DX60 S4 ETERNUS DX100 S4 ETERNUS DX200 S4 ETERNUS DX500 S4 ETERNUS DX600 S4 ETERNUS DX8900 S4	All version number	N	N	N	N
ETERNUS DX60 S3	All version number	N	N	N	N
ETERNUS DX100 S3 ETERNUS DX200 S3 ETERNUS DX500 S3 ETERNUS DX600 S3	All version number	N	N	N	N
ETERNUS DX8700 S3 ETERNUS DX8900 S3	All version number	N	N	N	N
ETERNUS DX200F	-	N	N	N	N
ETERNUS AF S3 series ETERNUS AF S2 series ETERNUS AF series	-	N	N	N	N
ETERNUS DX60 S2	V20L10-V20L16	Y	Y	Y	Y
ETERNUS DX80 S2 ETERNUS DX90 S2 ETERNUS DX400 S2 series	V10L11-V10L22	Y	Y	Y	Y
	V10L25	Y *1	Y	Y	Y
	V10L31	Y *1,2,3,4,5	Y *5	Y *5	Y
	V10L35	Y *1,2,3,4,5,6	Y *5,6	Y *5,6	Y
	V10L40	Y *1,2,3,4,5,6,7	Y *5,6,7	Y Apply patch Refer to Table 2 *5,6	Y
	V10L45-V10L47	Y *1,2,3,4,5,6,7,8,9	Y *5,6,7,8,9	Y Apply patch Refer to Table 2 *5,6,9	Y *9
	V10L50-V10L60	Y *1,2,3,4,5,6,7,8,9,10,11	Y *5,6,7,8,9,10,11	Y Apply patch Refer to Table 2 *5,6,9,10,11	Y *9,10,11
ETERNUS DX8000 S2 series	V10L23-V10L24	Y	Y	Y	Y
	V10L25	Y *1	Y	Y	Y
	V10L31	Y *1,2,3,4,5	Y *5	Y *5	Y
	V10L35	Y *1,2,3,4,5,6	Y *5,6	Y *5,6	Y
	V10L40	Y *1,2,3,4,5,6,7	Y *5,6,7	Y *5,6	Y
	V10L45-V10L47	Y *1,2,3,4,5,6,7,8,9	Y *5,6,7,8,9	Y Apply patch Refer to Table 2 *5,6,9	Y *9
	V10L50-V10L60	Y *1,2,3,4,5,6,7,8,9,10,11	Y *5,6,7,8,9,10,11	Y Apply patch Refer to Table 2 *5,6,9,10,11	Y *9,10,11
ETERNUS DX60 ETERNUS DX80	V10L11-V10L72	Y	Y	Y	Y
ETERNUS DX90	V10L31-V10L72	Y	Y	Y	Y
ETERNUS DX400 series ETERNUS DX8000 series	V20L41	N	N	N	N
	V20L50-V20L86	Y	Y	Y	Y
Tintri VMstore series/ETERNUS TR series	TxOS 3.2.2.1-	N	N	N	N
ETERNUS8000 model 700 ETERNUS8000 model 900 ETERNUS8000 model 1100 ETERNUS8000 model 2100 ETERNUS4000 model 300 ETERNUS4000 model 500	V10L10-V10L81	Y	Y	Y	Y
	V11L10-V11L96	Y	Y	Y	Y

ETERNUS8000 model 800 ETERNUS8000 model 1200 ETERNUS8000 model 2200 ETERNUS4000 model 400 ETERNUS4000 model 600	V20L10~V20L41	N	N	N	N
	V20L50~V20L86	Y	Y	Y	Y
ETERNUS2000 model 50 ETERNUS2000 model 100 ETERNUS2000 model 200	V10L10~V10L82	Y	Y	Y	Y

- *1:The UID display of the volume is unsupported.
- *2:Wide Striping Volume is unsupported.
- *3:ODX Buffer Volume is unsupported.
- *4:Encryption disk (SED) use for Flexible Tier is unsupported.
- *5:IPv6 address of device is unsupported.
- *6:IPv6 address of iSCSI port is unsupported.
- *7:FC 16Gbps is unsupported.
- *8:FC CA port link state transition notification is unsupported.
- *9:The setting related to BS2000 is unsupported.
- *10: Following setting and display of RA port is unsupported.
 - REC line number
 - REC transfer mode
- *11:Following setting and display of host response is unsupported.
 - TPG Referrals
 - iSCSI Reservation Range

Note .

Because bug fix is included in the patch, the application of the latest patch is recommended regardless of the presence of the support.

- *1:ボリュームのUID表示は未サポート
- *2:Wide Striping Volume は未サポート
- *3:ODX Buffer Volume は未サポート
- *4:Flexible Tier の暗号化ディスク(SED)利用は未サポート
- *5:装置のIPv6アドレスは未サポート
- *6:iSCSIポートのIPv6アドレスは未サポート
- *7:FC 16Gbps は未サポート
- *8:FC CAポートリンク状態遷移通知は未サポート
- *9:BS2000関連設定は未サポート
- *10:RAポートの以下の設定/表示は未サポート
 - REC回線番号
 - REC転送モード
- *11:ホストレスポンスの以下の設定/表示は未サポート
 - TPG Referrals
 - iSCSI リザベーション単位

留意事項1

パッチには障害修正も含まれているため、サポートの有無に関わらず最新パッチの適用を推奨します。

Table 2. patch number

ETERNUS SF Storage Cruiser Version	Model Name	Firmware Version	patch number			
			Solaris	Windows	Linux (RHEL5 x64)	Linux (Others)
ETERNUS SF Storage Cruiser 15.2	ETERNUS DX80 S2 ETERNUS DX90 S2 ETERNUS DX400 S2 series	V10L40	T007788SP-01 or later T007824SP-01 or later	T007787WP-01 or later T007816WP-01 or later	T007789LP-01 or later T007826LP-01 or later	T007789LP-01 or later T007825LP-01 or later
		V10L45~V10L47	T007788SP-01 or later T007824SP-01 or later	T007787WP-01 or later T007816WP-01 or later	T007789LP-01 or later T007825LP-01 or later 6	T007789LP-01 or later T007825LP-01 or later
		V10L50	T007788SP-01 or later T007824SP-01 or	T007787WP-01 or later T007816WP-01 or	T007789LP-01 or later T007826LP-01 or later	T007789LP-01 or later T007825LP-01 or
	ETERNUS DX8000 S2 series	V10L45~V10L47	T007788SP-01 or later T007824SP-01 or later	T007787WP-01 or later T007816WP-01 or later	T007789LP-01 or later T007826LP-01 or later	T007789LP-01 or later T007825LP-01 or later
		V10L50	T007788SP-01 or later T007824SP-01 or later	T007787WP-01 or later T007816WP-01 or later	T007789LP-01 or later T007826LP-01 or later	T007789LP-01 or later T007825LP-01 or later