



PRIMERGY CUSTOMER INFORMATION BULLETIN

Number/Revision:

PY-CIB064-00

Issue Date:

March 04, 2021

Title:

ESXi 7.0 Cannot Install on BU100 - Error Connection Time Out

Applies to:

- Hardware
 - PRIMERGY CX2550 M4
 - PRIMERGY RX1330 M4
 - PRIMERGY RX2520 M4/M5
 - PRIMERGY RX2530 M4/M5
 - PRIMERGY RX2540 M4/M5/M6
 - PRIMERGY RX4770 M4/M5/M6
 - PRIMERGY TX1320 M3/M4
 - PRIMERGY TX1330 M4
 - PRIMERGY TX2550 M4/M5

- Operating System
 - VMware vSphere ESXi version 7.0 or later

Effective Duration:

Permanent

Problem:

Multiple error messages are logged in dmesg and vmkernel.log every 30sec during ESXi 7.0 installation on BU100.

The issue is known by VMware: <https://kb.vmware.com/s/article/81206>

Cause:

Failed to make the partition by the installer of ESXi7 during installation, due to missing signal for being ready to write.



PRIMERGY CUSTOMER INFORMATION BULLETIN

Solution:

Update the firmware for the FX3S to 0x19 on the BU100. This firmware can be downloaded from the download site: <https://support.ts.fujitsu.com>

Direct download link:

<https://support.ts.fujitsu.com/IndexDownload.asp?SoftwareGuid=83644DE0-00D0-41F3-9CFA-C1CDAFB3D293>

Important:

Please review the Important Information field when downloading the firmware.

Determine Installed Version: (1.7 = 0x17)

✔ Mass Storage

^ ✔ Storage Controllers

Status	Product
✔ OK	Dual microSD 64GB Enterprise (1)
Ports	2
Protocol	USB
Vendor	Fujitsu Limited
Serial Number	39B001146724AEAE1F437056041900F5
PCI Vendor and Device ID	0BF8 / 1029
Controller firmware version	1.5 (LPC), 1.7 (FX3S)
Alarm present	No
SMART Support	Disabled
Correctable Errors	0
Uncorrectable Errors	0

Preliminary step:

Offline update tool is provided as an iso file.

You can use one of the below methods to mount/boot the iso image:

1. AVR (Advanced Video Redirection) session to mount iso file and boot.
 2. CD/DVD drive.
 3. Prepare USB pen drive (see additional information).
-



PRIMERGY CUSTOMER INFORMATION BULLETIN

Update procedure:

Boot the offline update tool.

Press 2 to update firmware.

```
Dual microSD 64GB Enterprise Firmware Update tool V1.0L01
Firmware Package LPC_15 FX3S_19
Copyright 2021 FUJITSU LIMITED

Please select:
 1: List Devices
 2: Update firmware
 3: Reboot system
 4: Shutdown system

Select: _
```

Type Yes, and press the Enter key to confirm the firmware update:

```
Select: 2
Do you want to firmware update? (Yes/No) > Yes
```

When the update has been finished successfully -> Press enter key:

```
Flashtool linflpic returned : 0
```

```
STEP 5 : Flashing firmware for both devices OK -----
```

```
-----
exit 0
```

```
Push enter key to continue
```



PRIMERGY CUSTOMER INFORMATION BULLETIN

Press 4 and Enter key to shut down the server:

```
Dual microSD 64GB Enterprise Firmware Update tool V1.0L01
Firmware Package LPC_15 FX3S_19
Copyright 2021 FUJITSU LIMITED

Please select:
 1: List Devices
 2: Update firmware
 3: Reboot system
 4: Shutdown system

Select: _
```

Power on server and boot from the offline update tool again.

Press 1 and list the devices to make sure that the software version for BU100 FX3S is 0x19

```
Select: 1

PIC-File-name PIC-Status PIC-ID HW-Version SW-Version Description-name
0xd9:1 brg01_15.hex OK 0x49 0x0a 0x15 BU100 LPC
0xd9:2 rai00_19.hex OK 0x4d 0x02 0x19 BU100 FX3S
Push enter key to continue
```

Additional Information:

Prepare USB pen drive with diskpart:

Open Microsoft Windows command prompt with administrator rights and type:

- diskpart
- list disk
- select disk x (x is the usb pen drive)
- clean
- create partition primary
- select partition 1
- active
- format quick fs=fat32
- assign
- exit

Extract the iso file or mount the iso image and copy the whole content to the USB pen drive.



PRIMERGY CUSTOMER INFORMATION BULLETIN

Revision History:

REVISION	DATE	CHANGE SUMMARY
000	March 04, 2021	Initial Release