

## ScanSnap S510 for Specifications

General technical specifications for the ScanSnap S510:

For any further questions or queries please contact our scanner technical support team on +44 (0) 20 8573 4444

Product name		ScanSnap S510
<b>General Technical Specifications</b>		
<b>Scanner Type</b>		ADF (Automatic Document Feeder), Duplex color scanning
<b>Output</b>		Color/B&W/Automatic color and B&W detection
<b>Image Sensor</b>		Color CCD x 2
<b>Optical Resolution</b>		600 dpi
<b>Scanning Speed (A4)</b>	<b>Normal mode</b>	Color 150dpi, B&W 300dpi: 18 pages per minute/36 images per minute
	<b>Better mode</b>	Color 200dpi, B&W 400dpi: 12 pages per minute/24 images per minute
	<b>Best mode</b>	Color 300dpi, B&W 600dpi: 6 pages per minute/12 images per minute
	<b>Excellent mode</b>	Color 600dpi, B&W 1,200dpi: 0.6 pages per minute/1.2 images per minute
<b>Scanning Range</b>		A4, A5, A6, B5, B6, Business card, Letter, Legal and Custom sizes (can set for up to 5 different paper types)/Automatically recognizes paper type by paper length Use of Carrier sheet permits the scanning of A3, B4, double letter and photographs as well as those listed above
<b>Paper Weight (thickness)</b>		52 to 127g/m (14 to 34 lb)
<b>Hopper Capacity</b>		50 Sheets (20lb)
<b>Interface</b>		USB 2.0 (USB 1.1 Compatible)
<b>Driver</b>		ScanSnap Specific Driver <sup>(1)</sup> (TWAIN/ISIS® not supported)
<b>Applications</b>		Adobe Acrobat 8.0 Standard, (Win 2000/XP/Vista only) ABBYY FineReader for ScanSnap 2.0, CardMinder™ v3.1, ScanSnap Organizer v3.1
<b>Compatible Operating System</b>		WIN 98SE/2000/XP/Vista
<b>Power Requirement</b>		AC 100 to 240V, 50/60 Hz
<b>Power Consumption</b>		Scan mode: 28W or less, Sleep mode: less than 6W
<b>Operation Environment</b>	<b>Temperature</b>	5°C to 35°C (42°F to 95°F)
	<b>Relative humidity</b>	20 to 80% (non-condensing)
<b>Dimensions (W x D x H)</b>		284 x 157 x 158 (11.2 x 6.2 x 6.2 in.)
<b>Device Weight</b>		5.9lbs. or less, without power adapter
<b>Environmental Compliance</b>		ENERGY STAR® Compliant
<b>Limited Warranty</b>		1 year Limited Warranty. For full details, visit the warranties page or call +44 (0) 870 6000 922
<b>Service Options</b>		Advanced Exchange Upgrade – Advanced Exchange Upgrade Plus. For full details on all service programs, visit <a href="http://www.fel.fujitsu.com/assurance">www.fel.fujitsu.com/assurance</a>
<b>Part Number</b>		PA03360-B505

<sup>1</sup> Twain or ISIS applications cannot be used directly.

### Compatible Operating Systems

	Win® 98	Win® 98 2nd Ed	Win® Me	Win® 2000 Pro	Win® XP SP1	Win® Vista
<b>ScanSnap Manager V4.1</b>	✓	✓	✓	✓	✓	✓
<b>ScanSnap Organizer V3.1</b>	✓	✓	✓	✓	✓	✓
<b>CardMinder™ V3.1</b>	✓	✓	✓	✓	✓	✓
<b>Adobe® Acrobat® 8.0 Standard(2)</b>	X	X	X	✓	✓ <sup>1</sup>	✓ <sup>1</sup>
<b>ABBYY FineReader for ScanSnap™ 2.0</b>	✓	✓	✓	✓	✓	✓

1 Compatible with Windows® 2000 Professional (Service Pack 2 or higher) and Windows® XP Professional / Home Edition.

2 Requires Microsoft® Internet Explorer 5.5 or higher.

### Hardware Requirements(2)

Requirement	Specifications
<b>CPU</b>	Intel® Pentium® III processor 600MHz or higher (Intel® Pentium® 4 processor 1.8GHz or higher is recommended)
<b>Memory Capacity(1)</b>	128MB or higher (256MB or higher recommended)
<b>Optical resolution</b>	800 x 600 dots or higher
<b>Disk Capacity</b>	Spare capacity of at least 1,080MB is necessary to install the software that is included in this chart.(3)
<b>CD-ROM Drive</b>	Required for installation
<b>USB Port</b>	USB2.0/USB1.1

1 A memory capacity of 512MB or higher is recommended when scanning in "Excellent mode".

2 Scanning speeds may drop if recommended CPU, memory capacity and USB1.1 requirements are not met.

3 Installing Adobe® Acrobat® 7.0 in addition to the other software included with this scanner will require additional 300MB in File Cache memory.