



# LifeBook S-4530/S-4532

- Intel® Pentium® III Processor 500MHz
- Modular mobile slot for digital camera, PC Card slot, DVD/CD-ROM, CD-R/RW, SuperDisk & 2nd Battery
- Built-in 10/100Mbps LAN & V.90 modem
- 1.7kg light (with weight saver), B5 file size
- Programmable Application Launcher Buttons

## S-4530

## S-4532

<b>CPU</b>	Intel® Pentium® III processor 500MHz (w/ SpeedStep™)	
<b>Secondary Cache</b>	256KB	
<b>Memory</b>	64MB SDRAM, max 256MB	128MB SDRAM, max 256MB
<b>Hardisk Drive</b>	9GB	9GB
<b>Flash ROM</b>	512KB flash memory	
<b>Chipset</b>	Intel® 440MX	
<b>Display</b>	12.1" SVGA TFT colour	12.1" XGA TFT colour
<b>Graphics</b>	2.5MB video memory	
<b>Sound</b>	SoundBlaster® Pro-compatible with 3D internal speakers (stereo), internal microphone	
<b>Communication</b>	V.90 modem & 10/100Mbps LAN (built-in)	
<b>External I/O Interface</b>	1 x PCMCIA, 1 x USB, 1 x VGA, 1 x RJ-11, 1 x RJ-45, audio (line-in, microphone, headphone)	
<b>Port Replicator</b>	1 x external keyboard, 1 x external mouse, 1 x serial, 1 x parallel, 1 x USB, 1 x VGA, 1 x RJ-45, 1 x external FDD interface, AC adapter power input	
<b>Mobile Slot</b>	Supports: SuperDisk (standard) CD-ROM (standard) Replaceable with options : Digital Camera DVD Drive CD-R/RW Drive 2nd Battery PC Card Slot Weight Saver	Supports: CD-R/RW (standard) Replaceable with options : Digital Camera DVD Drive SuperDisk Drive 2nd Battery PC Card Slot Weight Saver
<b>Quick Touch Button</b>	Programmable application launcher buttons for Internet, email and two other software	
<b>Digital Camera</b>	Optional (USB type)	
<b>Pointing Device</b>	Touch Pad	
<b>IR Interface</b>	IrDA1.1 (4Mbps max)	
<b>PCMCIA Interface</b>	Type I or II x 1 slot	
<b>AC Adapter</b>	AC 100-220V / DC16V 2.5A	
<b>Battery</b>	3.3 hours** Li-ION 10.8V 2600mAH	
<b>OS Bundled</b>	Microsoft Windows® 98	
<b>OS Supported</b>	Microsoft Windows® 98 Microsoft Windows® 2000 Professional	
<b>Dimensions</b>	Approx. 288mm (W) x 226.5mm (D) x 23.5mm (H)	
<b>Weight</b>	Approx. 1.7kg (with battery and weight saver)	

\*\* Results obtained from ZD BatteryMark3.0. Actual times may vary depending on use, configuration and system load.



All rights to the mentioned trademarks reside with their respective owners. Fujitsu endeavours to ensure that the information in this documentation is correct and fairly stated, but does not accept liability for any errors or omissions. The development of Fujitsu products and services is continuous and published information may not be up to date. It is important to check the current position with Fujitsu. The document is not part of the contract or licence save in so far as may be expressly agreed.

Dealer:

### For further information, contact:

**SINGAPORE:**  
Fujitsu PC  
(Asia) Pte Ltd  
Tel: 65-776 0688  
Fax: 65-776 0788

**MALAYSIA:**  
Fujitsu PC  
(Asia) Pte Ltd  
(Malaysia Branch)  
Tel: 603-253 3997  
Fax: 603-253 4245

**THAILAND:**  
Fujitsu Systems  
Business (Thailand) Ltd  
PC Division  
Tel: 662-627 9021  
Fax: 662-627 9161

**PHILIPPINES:**  
Fujitsu Philippines Inc.  
Tel: 632-812 4001  
Fax: 632-817 7576

**INDONESIA:**  
PT Fujitsu Systems  
(Indonesia)  
Tel: 62-21 344 2601  
Fax: 62-21 344 2593

**VIETNAM:**  
Fujitsu Computer  
Systems of Vietnam Ltd  
Tel: 84-4-8313895-7  
Fax: 84-4-8313898