

## LifeBook S6130

- Intel® Centrino™ Mobile Technology
- Designed for Microsoft® Windows® operating systems
- Better performance with latest Intel® 855GME chipset and DDR333 memory modules
- Protect your investment with 1000/100/10Mbps<sup>4</sup> Gigabit Ethernet
- Superior security features for enhanced data and hardware protection
- Hot-swappable modular bay options



Fujitsu recommends Microsoft® Windows® XP Professional for Mobile Computing.

S6130 Recommended Configurations		
<b>Processor</b>	Intel® Pentium® M Processor 1.60GHz (w/Enhanced SpeedStep® Technology)	Intel® Pentium® M Processor 1.40GHz (w/Enhanced SpeedStep® Technology)
<b>OS Supported</b>	Microsoft® Windows® XP Home Edition Microsoft® Windows® XP Professional Edition Microsoft® Windows® 2000 Professional Edition	
<b>Display</b>	13.3" XGA TFT, 1024 x 768 pixels	13.3" XGA TFT, 1024 x 768 pixels
<b>Modular Bay Drive</b>	DVD/CD-RW Combo Drive	DVD/CD-RW Combo Drive
<b>Wireless LAN</b>	Intel® PRO/Wireless 2100 network connection 802.11b with Dual Antenna	Intel® PRO/Wireless 2100 network connection 802.11b with Dual Antenna
<b>Bluetooth™</b>	Integrated	-
<b>Memory</b>	512MB DDR333	256MB DDR333
<b>Hard Disk</b>	40GB	40GB
<b>Standard Battery Life</b>	Approx. 4.5hrs <sup>1</sup>	Approx. 4.7hrs <sup>1</sup>
<b>Weight</b>	Approx. 1.75kg (w/Weight Saver)	Approx. 1.75kg (w/Weight Saver)
Specifications		
<b>Chipset</b>	Intel® 855GME	
<b>Secondary Cache</b>	1MB	
<b>Max. Memory Supported</b>	2048MB DDR333	
<b>Hard Disk Drive</b>	Ultra DMA/100 and S.M.A.R.T support	
<b>Graphics</b>	Integrated Intel® Extreme Graphics 2 with DVMT <sup>2</sup> delivers low-power, high-performance 2D/3D graphics, video and display capabilities at a maximum shared memory of 64MB	
<b>Audio</b>	RealTek ALC202 AC97 codec with built-in Stereo Speakers OUT : Headphone-out IN : Microphone-in, Audio Line-in	
<b>Communication</b>	56K V.92 <sup>3</sup> modem, IrDA 1.1 4Mbps <sup>5</sup> , 1000/100/10Mbps <sup>4</sup> Gigabit Ethernet and Intel® PRO/Wireless 2100 network connection 802.11b with Dual Antenna Separate ON/OFF switch for wireless network connection	
<b>User Interface</b>	Keyboard: 82-key, 19mm key pitch, 3mm key stroke Touch Pad with Scroll Button	
<b>Card Slot</b>	PC Card Type I/II x 1, Smart Card support <sup>6</sup>	
<b>Connector Interface</b>	USB 2.0 x 2, VGA (external display), RJ45 (LAN), RJ11 (modem), Audio Line-in, IEEE1394, Headphone-out, Microphone-in, AC Power Input, Port Replicator Interface	
<b>Quick Launch Panel</b>	Four Programmable Application Launch Buttons (Internet, Email and two other software)	
<b>Security<sup>7</sup></b>	BIOS Lock, Hard Disk Lock, LifeBook Lock, Anti-theft Lock Slot, Smart Card <sup>6</sup>	
<b>Dimensions</b>	293mm (W) x 236.5mm (D) x 31.5mm min. (H)	
Bundled Accessories		
<b>AC Adapter</b>	Input AC 100~240V, Output DC 16V 60W	
<b>Software on CD</b>	Norman Virus Control & Norman Personal Firewall	
<b>Port Replicator</b>	Connector Interface: USB 2.0 x 2, VGA (external display), RJ45 (LAN), PS/2 (keyboard/mouse), Serial, Parallel, AC Power Input	
Optional		
<b>Modular Bay Options</b>	Replaceable with Bay Battery (Approx. 8.5hrs <sup>1</sup> - Standard + Bay batteries), DVD/CD-RW Combo Drive, DVD-ROM Drive, CD-RW Drive, Weight Saver	
<b>Floppy Disk Drive</b>	External USB 1.44MB FDD	
<b>Mouse</b>	USB Optical Scroll Mouse	

- <sup>1</sup> Results obtained from Ziff Davis (BusinessWinstone 2001) Battery Mark V4.0.1. Actual battery life will vary based on screen brightness, sound volume settings, running applications, connected peripherals, power management settings, battery conditioning, and other customer preferences. DVD or hard disk drive usage may also have a significant impact on battery life.
- <sup>2</sup> Dynamic Video Memory Technology (DVMT) dynamically responds to application requirement and efficiently allocates the proper amount of memory (max. 64MB) for optimal graphics and system performance. The memory size available to the Operating System will be less than the size of installed memory module.
- <sup>3</sup> Maximum 56Kbps performance varies according to your local service providers' services as well as line condition. V.92 performance is dependent on local service providers' services.
- <sup>4</sup> This term does not represent actual data rate of 1000/100/10Mbps and simply indicates compliance with IEEE 802.3, IEEE 802.3u and IEEE 802.3ab standards. Actual maximum data rate depends on network configurations, cable conditions as well as connected devices.
- <sup>5</sup> This term does not represent actual data rate of 4Mbps and simply indicates compliance with IrDA standard specification 1.1. Actual maximum data rate depends on local configurations and connected devices.
- <sup>6</sup> Smart Card support requires a Smart Card adapter for the PC Card Slot. This is available as an accessory. Fujitsu does not provide the application for Smart Card Solution.
- <sup>7</sup> BIOS Lock needs a supervisor/user password to access BIOS setup. BIOS settings can be configured to prompt for password at every first bootup or all bootup sequences. Access to BIOS setup is needed to configure Hard Disk Lock. Hard Disk Lock requires an access key to retrieve data on the hard disk. This is a Data Confidentiality security feature. LifeBook Lock requires supervisor/user password to bootup the LifeBook when it is powered up or resumes last session from suspend/hibernate mode. This is an anti-theft feature with more than 800,000 passwords combinations using the buttons on the Quick Launch Panel. Anti-theft Lock Slot allows the use of a lock to physically secure the LifeBook. SmartCard usage is dependent on customer's solution. Full security unlock sequence - LifeBook Lock, Bootup Lock (BIOS Lock), Hard Disk Lock. NOTE: Loss of password requires the LifeBook to be returned to Japan factory for system refresh. Cost of shipment and lost data will be borne by the customer.

It is natural for all thin-film transistor (TFT) liquid crystal displays (LCD) to show a small number of missing or discoloured dots. These are commonly known as non-conforming pixels. This is a technology limitation of TFT LCD and does not represent a defect. Fujitsu warranty does not cover limitations in technology such as non-conforming pixels. Specifications reflected above are engineering and hardware specifications. They do not represent actual usage or operating dimensions, sizes, performance and weights as these are dependent on factors such as operating temperature, type of operating system and applications used, connected devices and accessories as well as hardware configurations of the notebook.

All rights to the mentioned trademarks reside with their respective owners. Fujitsu endeavours to ensure that the information in this documentation is correct and fairly stated, but does not accept liability for any errors or omissions. The development of Fujitsu products and services is continuous and published information may not be up to date. It is important to check the current position with Fujitsu. The document is not part of the contract or licence save in so far as may be expressly agreed.

Dealer:

**SINGAPORE:**  
Fujitsu PC Asia  
Pacific Pte Ltd  
Tel : (65) 6776 0688  
Fax : (65) 6776 0788

**MALAYSIA:**  
Fujitsu PC Asia  
Pacific Pte Ltd  
Tel : (60-3) 2093 3997  
Fax : (60-3) 2093 4245

**HONG KONG:**  
Fujitsu PC  
Asia Pacific Ltd  
Tel : (852) 3101 8133  
Fax : (852) 3101 0633

**THAILAND:**  
Fujitsu Systems  
Business (Thailand) Ltd  
PC Division  
Tel : (66-2) 263 7888  
Fax : (66-2) 263 7880  
www.fujitsu-pcap.in.th

**AUSTRALIA:**  
Fujitsu PC Australia  
Toll Free: 1800 288 283  
Tel : (61-2) 9004 7455  
Fax : (61-2) 9004 7720  
www.lifebook.com.au

**CHINA:**  
Fujitsu PC China Division  
Tel : (86-21) 2890 9622  
Fax : (86-21) 2890 9999  
cn.fujitsu.com

**PHILIPPINES:**  
Fujitsu Philippines Inc.  
Tel : (63-2) 812 4001  
Fax : (63-2) 817 7576

**TAIWAN:**  
Fujitsu Taiwan Ltd  
Tel : (886-2) 2311 2255  
Fax : (886-2) 2311 2277

**VIETNAM:**  
Fujitsu Vietnam Ltd  
Tel : (84-4) 831 3895-7  
Fax : (84-4) 831 3898

**INDONESIA:**  
PT Fujitsu Systems  
(Indonesia)  
Tel : (62-21) 344 2601  
Fax : (62-21) 344 2593

**Note:** For countries not listed above, please contact our Singapore office.



BLUETOOTH is a trademark owned by its proprietor and used by Fujitsu under license.

www.pc-ap.fujitsu.com