#### **GPRS** Connection via Bluetooth using Singtel (e-ideas)



On your mobile phone, turn it to discoverable mode by performing the following steps:





Note: A small icon as shown above (see circled icon found in the above image) will appear once your T68 is in discoverable mode.

#### GPRS Connection via Bluetooth using Singtel (e-ideas)

Click on "Searching for Wireless Device" 2 icon and the list of Bluetooth devices in the vicinity will appear. Select T68 and the list of services available will appear

🔊 Pocket Plugfree	<b>4</b> £ 7:45 🔗	🎊 Pocket Plugfree	⊕ ◀€ 7:38	8
	Name	🧯 T68 🛛 🔫	Name	•
My Device		Audio Headset Servi Business Cards Internet Serial Port 1	ce	
Add 🐗 🏵 🔞		Connecting	E	≝ ^

Add Pocket LOOX to your list of **Paired devices** on the T68





Now, press the Yes button on T68

#### **GPRS** Connection via Bluetooth using Singtel (e-ideas)



	Add	to,	pa	ree	1
Pa	issk	ey:			
x	<b>k</b> okoł	(			

Enter any passkey on T68 then press Yes button.



Press Yes button

On your Pocket LOOX, you will be prompted to input the passkey, which is what you just entered on your T68.

Settings ◀< 8:18 🐽	Go to
Connections	Start Settings Connections Connections Connections R Dialing Locations.
When needed, automatically connect to The Internet using these settings: 00803746307A[DUN]	Connections & Diamig Locations.
Modify Connect	
When needed, automatically connect to Work using these settings:	
Work Settings	
Modity Connect	
Work	
Connections Dialing Locations	
E = 1 = 1 = 1 = 1 = 1 = 1 = 1 = 1 = 1 =	

🎊 Settings 🛛 📢 10:59 🐽	Enter Country Code : 65
Connections	Click <b>Dialing Patterns</b>
Location: Work 🔻	
New Remove	
Local Settings	
Area code: 🛛 🛞 Tone dialing	
Dialing Patterns	
Connections Dialing Locations	
▲	
🔎 Settings 🚽 🛃 11:04 🔞	Under <b>Dialing Patterns</b> , enter the
Dializa Battaras	following accordingly:
	For local Calls, dial "G"
For local calls, dial:	For Long Distance calls, dial "01FG"
G	For international calls, dial 001EFG,
For long distance calls, dial:	Tap on OK to exit Draining Fatterins
loo1EES	
(E,e = country code; F,t = area code; G,g = number)	
Edit 🔤 🔺	

🌮 Settings 🛛 📢 8:18 🐽	Select Connections
Connections	Under the section:
When needed, automatically connect to The Internet using these settings: 00803746307A[DUN]	"When needed, automatically connect to the Internet using these settings": Select T68 address as shown
When needed, automatically connect to Work using these settings:	008038746307A[DUN] from the drop down menu
Modify Connect My network card connects to: Work	Then tap on " <b>Niodiry</b> "
Connections Dialing Locations	

🔊 Settings 🛛 📢 7:18 🐽	Click on <b>Modem</b> .
00803746307A[DUN]	Then tap and hold on your profile. Once drop down menu appears select <b>Connect</b>
Create a connection, or tap and hold on an existing connection and select a desired action.	drop down mend appears, select <b>connect.</b>
Name Number	
New	
When dialing: Automatically dial the best number	
General Modem Proxy Settings	

윤 Settings 🛛 📢 7:19	When prompted to
Make New Connection	"Enter a name for the connection": Select <b>00803746307A[DUN]</b> (T68 address)
Enter a name for the connection:	Select 115200 for Baud rate :
BT GPRS ST	and then, tap on the <b>Advanced</b> button
Select a modem:	
00803746307A[DUN]	
Baud rate: 115200  Advanced Cancel Back Next	
<b>₩</b>	

🎢 Settings 🛛 📢 7:29 🐽	Select "Use server-assigned IP address"
Advanced	Deselect Use software compression Deselect Use IP header compression
Use server-assigned IP address	Then tap on " <b>Name Servers</b> "
O Use specific IP address	-
Use Slip	
Use software compression	
Use IP header compression	
Port Settings TCP/IP Name Servers	

Settings	<b>∢</b> € 9:33 🛛 🔂
Jvanced         ) Use server-assigned address         ) Use specific server address         DNS:       165, 21, 83         Alt DNS:       165, 21, 100         WINS:       0, 0, 0         Alt WINS:       0, 0, 0         Alt WINS:       0, 0, 0         Year Settings       TCP/IP	ses 88 0 0 0 rvers

🌮 Settings	<b>4</b> € 7:19
Make New Connection	n
Enter a name for the cor	nnection:
BT GPRS ST	
Select a modem:	
00803746307A[DUN	] •
Baud rate: 115200 🔻	Advanced
Cancel	Back Next
	▲

🎢 Settings 🛛 📢	7:32	For Singapore, enter country code: 65
		Leave Area code blank
My Lonnection		Enter phone number :* <b>99</b> ***X#
Country code: 65		Tap on Next
Area code:		Note that <b>X</b> is CID number which can be
Phone number: *99***1#		found in your T68 Refer to <b>GPRS Setting</b>
		01 1 08.
Cancel Back	Next	

🎊 Settings	<b>4</b> € 7:33
My Connection	
<ul> <li>Cancel call if not connect</li> <li>120 seconds</li> <li>Wait for dial tone before</li> <li>Wait for credit card tone</li> <li>Extra dial-string modem con</li> </ul>	ted within e dialing seconds
Cancel Ba	ck Finish
	<b></b>

Settings	<b>4</b> € 8:02 @
00803746307A[DUN]	
Create a conne existing connect	ction, or tap and hold on an tion and select a desired action.
Name	Number
When dialing: /	n +65 *99***1# Automatically dial the best
General Moder	Proxy Settings
	<b>₩</b>

Settings         ◀€ 7:39         ⓓ<	Select "This network uses a proxy server to connect to the Internet"
<ul> <li>This network connects to the Internet</li> <li>This network uses a proxy server to connect to the Internet</li> <li>Proxy server:</li> <li>proxy.e-ideas.com.sg</li> <li>Advanced</li> </ul>	For Singtel subscribers, enter proxy server as follows: proxy.e-ideas.com.sg For other subscribers, please refer to your respective ISP providers for other proxy settings
General Modem Proxy Settings	Tap on <b>Advanced</b>

ह Settings 🛛 📢 9:27 🐽	Under Port, enter 8080
My Connection	Leave the rest of the parameters as default
Server Port	Tap on <b>OK</b> once the above is done
HTTP proxy.e-ideas.com.sg : 8080	
WAP	
Socks proxy.e-ideas.com.sg : 1080	
Type: 💿 Socks 4 🔵 Socks 5	
User ID	
Password	
▲ Image: A marked and a marked an	

🏂 Settings 🛛 📢 7:38 🐽	Tap on <b>Modem</b> at the same time holding
00803746307A[DUN]	on to profile
Create a connection, or tap and hold on an existing connection and select a desired action.	Once drop down menu appears, select Connect
Name Number	
New My Connection +65 *99***1# When dialing: Automatically dial the best number	
General Modem Proxy Settings	
<u>▲</u>	

B Logon to Network Ser ◄ 12:21	Enter your User Name as country code,
Network Log On	country code> <vour mobile="" no.="" phone=""></vour>
Resource: My Connection1	Eg. 6598754321
User name: Password: Domain: Save password OK Cancel	Enter your account <b>Password</b> (eg. e-ideas account password) Tap on <b>Save password.</b>

🎢 Settings 🛛 👫 📢 8:43 🐽	Connection will then be established
008037463074[DUN]	
Connecting	
Connecting to: My Connection . Dialing from: Work Using: 008037463074[DUN]	
Dialing *99***1#	
Change connection settings	
Hide End	
When dialings, Automatically dial the back	
number	
General Modem Proxy Settings	
View Tools 💠 🚱 🚰 🚞 🎦 🔤 📥	