

# ESPRIMO P5100

- Your everyday performer when Reliability, Performance and Expandability is your concern
- Ergonomic Features with USB and Audio connectors conveniently located
- Health and Environment friendliness with RoHS<sup>7</sup> compliance
- Expect more with Nero 7 Essentials with 13 modules for your innovative digital media creation



Recommended Configurations		
Processor <sup>1</sup>	Intel® Pentium® 4 Processor 630 (3GHz, 2MB L2 cache, 800MHz FSB)	Intel® Pentium® 4 Processor 516 (2.93GHz, 1MB L2 cache, 533MHz FSB)
OS Recommended	Genuine Windows® XP Professional	Genuine Windows® XP Home Edition
Display	Fujitsu 17" TFT LCD <sup>2</sup> Monitor	Fujitsu 17" CRT Flat Screen Colour Monitor
Graphics	Integrated SiS® Mirage™ 2D/3D Graphics Accelerator, Max 64MB VRAM (SMA)	
Memory	1024MB SDRAM	256MB SDRAM
Hard Disk	160GB, S-ATA, 7200rpm	80GB, S-ATA, 7200rpm
Optional Device	DVD Super Multi Writer <sup>3</sup>	52x CD-ROM
Specifications		
Processor Supported <sup>1</sup>	Intel® Pentium® 4 Processor 650/ 640/ 630/ 517 with HT Technology Intel® Pentium® 4 Processor 516 Intel® Celeron® D Processor 351/ 341/ 331	
OS Supported	Genuine Windows® XP Home Edition Genuine Windows® XP Professional	
System Bus Speed	800MHz/ 533MHz	
Maximum Memory Supported	2GB DDR400 SDRAM (2 Slots, 1GBx2)	
Chipset	SiS 661FX (North bridge), SiS964 MultiIOL® Media I/ O (South bridge)	
Hard Disk Drive	Serial ATA-150, S.M.A.R.T support, Two Partitions - 50/50 <sup>8</sup>	
Graphics	Integrated SiS® Mirage™ 2D/3D Graphics Accelerator, Max 64MB VRAM (SMA) Optional: ATI RADEON™ X1300 Discrete Graphics Card	
Audio	RealTek ALC655, Six channel audio codec designed for PC multimedia systems.	
Network Interface	RealTek RTL8100C, 10/100Mbps <sup>4</sup>	
Security <sup>5</sup>	BIOS Lock, Hard Disk Lock, Anti-theft Lock Slot	
Connector Interface	Serial Port x 1 (9-pin, FIFO, 16550-compatible) Parallel Port x 1 (25-Pin, EPP/ ECP) USB 2.0 x 8 (Front x 2, Rear x 4, Internal x 2) PS/ 2 Keyboard Port x 1 PS/ 2 Mouse Port x 1 RJ45 x 1 VGA x 1 Audio (Rear): Mic-in x 1, Line-out x 1, Line-in x 1 Audio (Front): Mic-in x 1, Headphone-out x 1	
Keyboard & Mouse	PS/ 2 Keyboard and USB Optical Mouse	
Expansion Slots [Free]	PCI Slot [3] AGP Slot [1]	
Drive Bays [Free]	Front Access: 3.5" x 2 [2], 5.25" x 2 [1]	
Power	AC200-240V 50/ 60Hz Max output of power supply: 300W	
Dimensions	Approximately 180mm(W) x 380mm(D) x 365mm(H) (25L)	
Optional		
Floppy Disk Drive	1.44MB FDD	
Discrete Video Card	ATI RADEON® X1300 Discrete Graphics Card	
Modem	V.92 Compliant 56K Internal Data/ Fax Modem card	
Memory Card Reader	11-in-1 Flash Memory Card Reader	
Bundled Software		
Bundled Software	For DVD Super Multi Writer: Bundled with Nero 7.0 Suite 2 <sup>6</sup> Fujitsu Hardware Diagnostic Tool, Adobe Acrobat Reader 6.0	
Software on CD	1 year Full Licensed Norman Virus Control with Sandbox Technology and Norman Personal Firewall Acronis True Image 8.0 Personal Edition	

#### SINGAPORE:

**Fujitsu PC Asia Pacific Pte Ltd**  
Tel : (65) 6776 0688  
Fax : (65) 6776 0788

#### MALAYSIA:

**Fujitsu PC Asia Pacific Pte Ltd**  
Tel : (60-3) 2093 3997  
Fax : (60-3) 2093 4245

#### HONG KONG:

**Fujitsu PC Asia Pacific Ltd**  
Tel : (852) 3101 8133  
Fax : (852) 3101 0633

#### THAILAND:

**Fujitsu Systems Business (Thailand) Ltd PC Division**  
Tel : (66-2) 263 7888  
Fax : (66-2) 263 7880

#### AUSTRALIA & NEW ZEALAND:

**Fujitsu PC Australia**  
Toll Free: 1800 288 283  
Tel : (61-2) 8877 9500  
Fax : (61-2) 9889 3360  
[www.lifebook.com.au](http://www.lifebook.com.au)

#### CHINA:

**Fujitsu PC China Division**  
Tel : (86-21) 3310 0808  
Fax : (86-21) 3310 0606  
[cn.fujitsu.com/pc](http://cn.fujitsu.com/pc)

#### PHILIPPINES:

**Fujitsu Philippines Inc.**  
Tel : (63-2) 812 4001  
Fax : (63-2) 817 7576

#### TAIWAN:

**Fujitsu Taiwan Ltd**  
Tel : (886-2) 2311 2255  
Fax : (886-2) 2311 2277

#### VIETNAM:

**Fujitsu Vietnam Ltd**  
Tel : (84-4) 831 3895  
Fax : (84-4) 831 3898

#### INDONESIA:

**PT. Fujitsu Indonesia**  
Tel : (62-21) 570 9330  
Fax : (62-21) 573 5150

#### INDIA:

**Fujitsu India Limited**  
Tel : (91-11) 2370 6070  
Fax : (91-11) 2370 6079

Note: For countries not listed above, please contact our Singapore office.

The above information shows the general technical specifications of the product and does not represent actual configuration. For specific configurations and their availability, please check with your local distributors.

- Processor definitions: Intel® Pentium 4 Processor 630 (3GHz HT, 2MB L2 cache, 800MHz FSB); Intel® Pentium 4 Processor 640 (3.20GHz HT, 2MB L2 cache, 800MHz FSB); Intel® Pentium 4 Processor 650 (3.40GHz HT, 2MB L2 cache, 800MHz FSB); Intel® Pentium 4 Processor 517 (2.93GHz HT, 1MB L2 cache, 533MHz FSB); Intel® Pentium 4 Processor 516 (2.93GHz, 1MB L2 cache, 533MHz FSB); Intel® Celeron® D Processor 341 (2.93GHz, 256KB L2 cache, 533MHz FSB); Intel® Celeron® D Processor 351 (3.20GHz, 256KB L2 cache, 533MHz FSB)
- It is natural for all liquid crystal displays (LCD) to show a small number of missing or discoloured pixels. These are commonly known as non-conforming pixels. This is a technology limitation of LCD and does not represent a defect. Fujitsu warranty does not cover limitations in technology such as non-conforming pixels.
- Supports DVD multi formats such as DVD-RAM, DVD+R DL, DVD+R, DVD-R, DVD-ROM, CD-RW, CD-R, CD-ROM.
- This term does not represent actual data rate of 10/100Mbps and simply indicates compliance with IEEE 802.3, IEEE 802.3u and IEEE 802.3ab standards. Actual maximum data rate depends on network configurations, cable conditions as well as connected devices.
- BIOS Lock needs a supervisor/ user password to access BIOS setup. BIOS settings can be configured to prompt for password at every first bootup or all bootup sequences. Access to BIOS setup is needed to configure Hard Disk Lock. Hard Disk Lock requires an access key to retrieve data on the hard disk. This is a Data Confidentiality security feature. Anti-theft Lock Slot allows the use of a lock to physically secure the ESPRIMO.
- Bundled Nero 7 Essentials comprises of Nero Express 7 Essentials, Nero Startsmart 3 Essentials, Nero Scout, Nero Home Essentials Se, Nero Toolkit, Nero Coverdesigner 2 Essentials, Incd 5 Essentials, Nero Photosnap Viewer Essentials, Nero Vision 4 Essentials, Nero Backitup 2 Essentials, Nero Photoshowexpress 4, Nero Photosnap Essentials, Nero Mediahome Essentials, Nero Showtime 2 Essentials, Nero Record 2 Essentials.
- RoHS (Restriction on Hazardous Substances) compliance means the system and its internal components comply with the EU RoHS directive (2002/ 95/ EC) on the restricted use of six hazardous substances in the manufacture of the system and its internal components.
- This refers to Windows® XP hard disk drives C:\ and D:\ 50/50 refer to approximate 50% allocation of user accessible hard disk storage to C:\ and D:\ drives.

Specifications reflected above are engineering and hardware specifications. They do not represent actual usage or operating dimensions, sizes, performances and weights as these are dependent on factors such as operating temperature, type of operating system and application used, connected devices and accessories as well as hardware configurations of the desktop. Please check the compatibility of 3rd party accessories before purchase. Ambient temperature: 10° to 35°C, 10° to 60°C (non-operating). Relative humidity: 20% to 80% RH (operating and non-operating).



All rights to the mentioned trademarks reside with their respective owners. Fujitsu endeavours to ensure that the information in this documentation is correct and fairly stated, but does not accept liability for any errors or omissions. The development of Fujitsu products and services is continuous and published information may not be up to date. It is important to check the current position with Fujitsu. The document is not part of the contract or licence save in so far as may be expressly agreed.

Dealer: