# LifeBook C2220

- Mobile Intel® Pentium® 4 Processor M
- Designed for Microsoft® Windows® operating systems
- Fine graphics display with 15" SXGA+ TFT LCD
- Seamless Wi-Fi connectivity with integrated wireless LAN
- Mega storage with DVD-ReWritable drive option
- All-in-one design for greater convenience





	C2220 Recommended Configurations							
Processor	Mobile Intel® Pentium® 4 Processor 2.40GHz - M	Mobile Intel® Pentium® 4 Processor 2.20GHz - M	Mobile Intel® Pentium® 4 Processor 2.20GHz -					
	(w/Enhanced SpeedStep® Technology)	(w/Enhanced SpeedStep® Technology)	(w/Enhanced SpeedStep® Technology)					
OS Supported	Microsoft® Windows® XP Home Edition							
	Microsoft® Windows® XP Professional Edition							
	Microsoft® Windows® 2000 Professional Edition							
Display	15" Super XGA+ TFT, 1400 x 1050 pixels	14.1" XGA TFT, 1024 x 768 pixels	14.1" XGA TFT, 1024 x 768 pixels					
Optical Drive	DVD-RW Drive	DVD/CD-RW Combo Drive	DVD/CD-RW Combo Drive					
Wireless LAN	Atheros Wireless 54Mbps <sup>3</sup> network	Atheros Wireless 54Mbps <sup>3</sup> network	None					
	connection 802.11a/b/g <sup>7</sup> with Dual Antenna	connection 802.11a/b/g <sup>7</sup> with Dual Antenna						
Memory	256MB DDR266	256MB DDR266	256MB DDR266					
Hard Disk	60GB	40GB	40GB					
Standard Battery Life	Approx. 2.7hrs <sup>1</sup>	Approx. 3.2hrs <sup>1</sup>	Approx. 3.2hrs <sup>1</sup>					
Weight	Approx. 3.6kg	Approx. 3.6kg	Approx. 3.6kg					
	Specifications							
Chipset	ATI RADEON™ IGP340M + ALI M1535+							
Secondary Cache	512KB							
Max. Memory Supported	768MB DDR266							
Hard Disk Drive	Ultra DMA/100 and S.M.A.R.T Support							
Graphics	ATI RADEON™ IGP340M, selectable 32/64/128MB shared memory⁵ with 3D accelerator and AGP support							
Audio	SigmaTel STAC9767 AC97 codec with built-in Stereo Speakers							
	OUT : Headphone-out/SPDIF (Optical Digital out) IN : Microphone-in							
Communication	Communication 56K V.92 <sup>2</sup> modem, IrDA 1.1 4Mbps <sup>6</sup> , 100/10 Mbps <sup>4</sup> Fast Ethernet and Atheros Wireless 54Mbps <sup>3</sup> netwo							
	connection 802.11a/b/g <sup>7</sup> with Dual Antenna							
Separate ON/OFF switch for wireless network connection								
User Interface	Keyboard: 87-key, 19mm key pitch, 3mm key stroke							
	Touch Pad with Scroll Button							
Floppy Disk Drive	Built-in 1.44MB FDD							
Card Slot	PC Card Type I/II x 2/Type III x 1							
	SD Card/Memory Stick PRO x 1							
Connector Interface	USB 2.0 x 4, VGA (external display), RJ4	5 (LAN), RJ11 (modem), IEEE1394, S-Vide	o Out, Headphone-out/SPDIF, Serial,					
	1							

Results obtained from Ziff Davis (BusinessWinstone 2001) Battery Mark V4.0.1. Actual battery life will vary based on screen brightness, sound volume settings, running applications, connected peripherals, power management settings, battery conditioning, and other customer preferences. DVD or hard disk drive usage may also have a significant impact on battery life.

Maximum 56Kbps performance varies according to your local service providers' services as well as line condition. V.92 performance is also dependent on local service providers' services.

This term does not represent actual data rate of 54Mbps and simply indicates compliance with IEEE 802.119 and IEEE 802.111 standards. Actual maximum data rate depends on local network

Four Programmable Application Launch Buttons (Internet, Email and two other software)

- settings, configurations and connected devices.
- seturitys, corningurations and connected devices.

  This term does not represent actual data rate of 100/10Mbps and simply indicates compliance with IEEE 802.3 and IEEE 802.3 ustandards. Actual maximum network data rate depends on network configurations, cable conditions as well as connected devices.

  Memory allocation (max. 128MB) can be pre-set in the BIOS setup for optimal graphics and system performance. The memory size available to the Operating System will be less than the total size of installed memory modules.
- Actual maximum data rate depends on local network setings, configurations and connected devices.

**Bundled Accessories** 

Atheros 802.11a is only available for approved countries.

It is natural for all thin-film transistor (TFT) liquid crystal displays (LCD) to show a small number of missing or discoloured dots. These are commonly known as non-conforming pixels. This is a technology limitation of TFT LCD and does not represent a defect. Fujitsu warranty does not cover limitations in technology such as non-conforming pixels.

Specifications reflected above are engineering and hardware specifications. They do not represent actual usage or operating dimensions, sizes, performance and weights as these are dependent on factors such as operating temperature, type of operating system and applications used, connected devices and accessories as well as hardware configurations of the notebook.



**Quick Launch Panel** 

**Dimensions** 

AC Adapter

Software on CD







Parallel, Microphone-in, AC Power Input

Input: AC 100~240V, Output: DC 19V 80W

325.3mm (W) x 282mm (D) x 39.11mm min. (H)

Norman Virus Control & Norman Personal Firewall

Fuiitsu PC Asia Pacific Pte Ltd Tel: (65) 6776 0688 Fax: (65) 6776 0788

SINGAPORE:

MALAYSIA: Fuiitsu PC Asia Pacific Pte Ltd (Malaysia Branch)

Tel: (60-3) 2093 3997 Fax: (60-3) 2093 4245

HONG KONG: Fujitsu PC Asia Pacific Ltd Tel: (852) 3101 8133 Fax: (852) 3101 0633

THAILAND: Fujitsu Systems Business (Thailand) Ltd PC Division

Tel: (66-2) 263 7888 Fax: (66-2) 263 7880 www.fujitsu-pcap.in.th

# AUSTRALIA:

Fujitsu PC Australia Toll Free: 1800 288 283 Tel: (61-2) 9004 7455 Fax: (61-2) 9004 7720 www.lifebook.com.au

## CHINA:

Fujitsu PC China Division Tel: (86-21) 2890 9622 Fax: (86-21) 2890 9999 cn.fujitsu.com

### PHILIPPINES: Fujitsu Philippines Inc.

Tel: (63-2) 812 4001 Fax: (63-2) 817 7576

Fujitsu Taiwan Ltd Tel: (886-2) 2311 2255 Fax: (886-2) 2311 2277

## VIETNAM:

Fujitsu Vietnam Ltd Tel: (84-4) 831 3895~7 Fax: (84-4) 831 3898

### INDONESIA: PT Fujitsu Systems (Indonesia)

Tel: (62-21) 344 2601 Fax: (62-21) 344 2593

Note: For countries not listed above, please contact our Singapore

All rights to the mentioned trademarks reside with their respective owners. Fujitsu endeavours to ensure that the information in this documentation is correct and fairly stated, but does not accept liability for any errors or omissions. The development of Fujitsu products and services is continuous and published information may not be up to date. It is important to check the current position with Fujitsu. The document is not part of the contract or licence save in so far as may be expressly agreed.

Dealer:			