

## LifeBook P2120

- Transmeta Crusoe™ TM5800 (933MHz)
- Lower Power Consumption for Superior Battery Performance
- Brilliant Graphics Display with Wide Super XGA Panel
- External Display Connector
- Built-in Combo Drive (DVD & CD-R/RW) for Extra Flexibility



## P2120

|                        | . = . = .  |  |  |  |  |
|------------------------|--|--|--|--|--|
| CPU                    | Transmeta Crusoe™ TM5800 (933MHz)  |  |  |  |  |
| Secondary Cache        | 512KB  |  |  |  |  |
| System Bus Clock       | 133MHz   |  |  |  |  |
| Memory                 | 256MB SDRAM, max. 384MB (µDIMM, PC133)   |  |  |  |  |
| Hard Disk Drive        | 30GB (S.M.A.R.T. support)  |  |  |  |  |
| BIOS ROM               | 2MB Flash Memory   |  |  |  |  |
| Display                | 10.6" Wide Super XGA TFT Colour (Max. 1280 x 768 pixels)   |  |  |  |  |
| Graphics               | ATI Rage Mobility-M6C8, 8MB SDRAM (integrated) with 3D Graphics Accelerator                              |  |  |  |  |
| Sound                  | AC Link Audio (AC97 compliance: SigmaTel STAC9767 codec), Internal Speakers (Stereo)                     |  |  |  |  |
| Communication          | Integrated V.90 Modem & 10/100Mbps Base-T LAN  |  |  |  |  |
| Bluetooth™             | PC Card Option   |  |  |  |  |
| Device Bay             | Combo Drive (DVD & CD-R/RW)  |  |  |  |  |
|                        | Replaceable with options: 2nd Battery (6 cells, Li-lon, 10.8V, 3400mAH), Weight Saver, USB FDD (Bay Unit |  |  |  |  |
| External I/O Interface | 2 x USB 2.0, 1 x RJ11, 1 x RJ45, 1 x VGA**, IEEE1394, Video-out (S type), SPDIF (Optical-out),           |  |  |  |  |
|                        | Audio (Line-out, Headphone-out, Microphone-in), AC Adapter Power Input                                   |  |  |  |  |
| Quick Touch Panel      | Programmable launch buttons for email and two other software applications                                |  |  |  |  |
| Keyboard               | Key Pitch 17mm, Key Stroke 2mm   |  |  |  |  |
| Pointing Device        | QuickPoint with Scroll Button  |  |  |  |  |
| PCMCIA Interface       | Type I or II x 1 slot  |  |  |  |  |
| AC Adapter             | Input: AC100-240V, Output: DC16V 2.5A  |  |  |  |  |
| Battery                | Approx. 3.0 hours* (Standard battery pack: Li-Ion 10.8V 1900mAH)   |  |  |  |  |
|                        | Approx. 6.0 hours* (Optional extended battery pack: Li-Ion 10.8V 3800mAH)                                |  |  |  |  |
| OS Bundled             | Microsoft® Windows® XP Home Edition  |  |  |  |  |
| OS Supported           | Microsoft® Windows® 2000 Professional Edition  |  |  |  |  |
|                        | Microsoft® Windows® XP Home Edition  |  |  |  |  |
|                        | Microsoft® Windows® XP Professional Edition  |  |  |  |  |
| Other Software Bundled | Norman Virus Control   |  |  |  |  |
|                        | Norman Personal FireWall   |  |  |  |  |
| Dimensions             | 270mm(W) x 178mm(D) x 40.4mm(H)  |  |  |  |  |
| Weight                 | Approx. 1.5kg (with Combo Drive)   |  |  |  |  |

<sup>\*</sup> Results obtained from Ziff Davis (BusinessWinstone 2001) BatteryMark V4.0.1. Actual battery life will vary based on screen brightness, applications, features, power management settings, battery conditioning, and other customer preferences. DVD or hard drive usage may also have a significant impact on battery life.

\*\* VGA Out port requires a Fujitsu VGA Out cable that is included in the package.

It is natural for all thin-film transistor (TFT) liquid crystal displays (LCD) to show a small number of missing or discoloured dots. These are commonly known as non-conforming pixels. This is a technology limitation of TFT LCD and does not represent a defect. Fujitsu warranty does not cover limitations in technology such as non-conforming pixels

Some pictures are expressed in creative manners which may differ from the actual unit. Please check with your local distributor on any specifics.



Fujitsu PCs use genuine Windows® Operating Systems www.microsoft.com/piracy/howtotell

reside with their respective owners. Fujitsu endeavours to ensure that the information in this documentation is correct and fairly stated, but does not accept liability for any errors or omissions. The development of Fujitsu products and services is continuous and published information may not be up to date. It is important to check the current position with Fujitsu. The document is not part of the contract or licence save in so far as may be expressly agreed.

All rights to the mentioned trademarks



BLUETOOTH is a trademark owned by its proprietor and used by Fujitsu under license.

SINGAPORE: Fujitsu PC Asia Pacific Pte Ltd Tel: (65) 6776 0688 Fax: (65) 6776 0788

MALAYSIA: Fujitsu PC Asia Pacific Pte Ltd (Malaysia Branch) Tel: (60-3) 2093 3997 Fax: (60-3) 2093 4245

HONG KONG: Fujitsu PC Asia Pacific Ltd Tel: (852) 3101 8133 Fax: (852) 3101 0633

THAILAND: Fujitsu Systems
Business (Thailand) Ltd
PC Division
Tel: (66-2) 658 0350
Fax: (66-2) 658 0356 AUSTRALIA:
Fujitsu PC Australia
Toll Free: 1800 288 283
Tel : (61-2) 9004 7455
Fax : (61-2) 9004 7720
www.lifebook.com.au

PHILIPPINES: Fujitsu Philippines Inc. Tel: (63-2) 812 4001 Fax: (63-2) 817 7576

Dealer:

VIETNAM: Fujitsu Vietnam Ltd Tel: (84-4) 831 3895~7 Fax: (84-4) 831 3898 INDONESIA: PT Fujitsu Systems (Indonesia) Tel: (62-21) 344 2601 Fax: (62-21) 344 2593