

# SPARC Enterprise T2000 Server

**Overview Guide** 







# SPARC<sup>®</sup> Enterprise T2000 Server Overview Guide

Manual Code : C120-E373-01EN Part No. 875-4049-10 April 2007 Copyright 2007 Sun Microsystems, Inc., 4150 Network Circle, Santa Clara, California 95054, U.S.A. All rights reserved.

FUJITSU LIMITED provided technical input and review on portions of this material.

Sun Microsystems, Inc. and Fujitsu Limited each own or control intellectual property rights relating to products and technology described in this document, and such products, technology and this document are protected by copyright laws, patents and other intellectual property laws and international treaties. The intellectual property rights of Sun Microsystems, Inc. and Fujitsu Limited in such products, technology and this document include, without limitation, one or more of the United States patents listed at http://www.sun.com/patents and one or more additional patents or patent applications in the United States or other countries.

This document and the product and technology to which it pertains are distributed under licenses restricting their use, copying, distribution, and decompilation. No part of such product or technology, or of this document, may be reproduced in any form by any means without prior written authorization of Fujitsu Limited and Sun Microsystems, Inc., and their applicable licensors, if any. The furnishing of this document to you does not give you any rights or licenses, express or implied, with respect to the product or technology to which it pertains, and this document does not contain or represent any commitment of any kind on the part of Fujitsu Limited or Sun Microsystems, Inc., or any affiliate of either of them.

This document and the product and technology described in this document may incorporate third-party intellectual property copyrighted by and/or licensed from suppliers to Fujitsu Limited and/or Sun Microsystems, Inc., including software and font technology.

Per the terms of the GPL or LGPL, a copy of the source code governed by the GPL or LGPL, as applicable, is available upon request by the End User. Please contact Fujitsu Limited or Sun Microsystems, Inc.

This distribution may include materials developed by third parties.

Parts of the product may be derived from Berkeley BSD systems, licensed from the University of California. UNIX is a registered trademark in the U.S. and in other countries, exclusively licensed through X/Open Company, Ltd.

Sun, Sun Microsystems, the Sun logo, Java, Netra, Solaris, Sun StorEdge, docs.sun.com, OpenBoot, SunVTS, Sun Fire, SunSolve, CoolThreads, J2EE, and Sun are trademarks or registered trademarks of Sun Microsystems, Inc. in the U.S. and other countries.

Fujitsu and the Fujitsu logo are registered trademarks of Fujitsu Limited.

All SPARC trademarks are used under license and are registered trademarks of SPARC International, Inc. in the U.S. and other countries. Products bearing SPARC trademarks are based upon architecture developed by Sun Microsystems, Inc.

SPARC64 is a trademark of SPARC International, Inc., used under license by Fujitsu Microelectronics, Inc. and Fujitsu Limited-

The OPEN LOOK and Sun<sup>™</sup> Graphical User Interface was developed by Sun Microsystems, Inc. for its users and licensees. Sun acknowledges the pioneering efforts of Xerox in researching and developing the concept of visual or graphical user interfaces for the computer industry. Sun holds a non-exclusive license from Xerox to the Xerox Graphical User Interface, which license also covers Sun's licensees who implement OPEN LOOK GUIs and otherwise comply with Sun's written license agreements.

United States Government Rights - Commercial use. U.S. Government users are subject to the standard government user license agreements of Sun Microsystems, Inc. and Fujitsu Limited and the applicable provisions of the FAR and its supplements.

Disclaimer: The only warranties granted by Fujitsu Limited, Sun Microsystems, Inc. or any affiliate of either of them in connection with this document or any product or technology described herein are those expressly set forth in the license agreement pursuant to which the product or technology is provided. EXCEPT AS EXPRESSLY SET FORTH IN SUCH AGREEMENT, FUJITSU LIMITED, SUN MICROSYSTEMS, INC. AND THEIR AFFILIATES MAKE NO REPRESENTATIONS OR WARRANTIES OF ANY KIND (EXPRESS OR IMPLIED) REGARDING SUCH PRODUCT OR TECHNOLOGY OR THIS DOCUMENT, WHICH ARE ALL PROVIDED AS IS, AND ALL EXPRESS OR IMPLIED CONDITIONS, REPRESENTATIONS AND WARRANTIES, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT, ARE DISCLAIMED, EXCEPT TO THE EXTENT THAT SUCH DISCLAIMERS ARE HELD TO BE LEGALLY INVALID. Unless otherwise expressly set forth in such agreement, to the extent allowed by applicable law, in no event shall Fujitsu Limited, Sun Microsystems, Inc. or any of their affiliates have any liability to any third party under any legal theory for any loss of revenues or profits, loss of use or data, or business interruptions, or for any indirect, special, incidental or consequential damages, even if advised of the possibility of such damages.

DOCUMENTATION IS PROVIDED "AS IS" AND ALL EXPRESS OR IMPLIED CONDITIONS, REPRESENTATIONS AND WARRANTIES, INCLUDING ANY IMPLIED WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT, ARE DISCLAIMED, EXCEPT TO THE EXTENT THAT SUCH DISCLAIMERS ARE HELD TO BE LEGALLY INVALID.



Copyright 2007 Sun Microsystems, Inc., 4150 Network Circle, Santa Clara, California 95054, Etats-Unis. Tous droits réservés.

Entrée et revue tecnical fournies par FUJITSU LIMITED sur des parties de ce matériel.

Sun Microsystems, Inc. et Fujitsu Limited détiennent et contrôlent toutes deux des droits de propriété intellectuelle relatifs aux produits et technologies décrits dans ce document. De même, ces produits, technologies et ce document sont protégés par des lois sur le copyright, des brevets, d'autres lois sur la propriété intellectuelle et des traités internationaux. Les droits de propriété intellectuelle de Sun Microsystems, Inc. et Fujitsu Limited concernant ces produits, ces technologies et ce document comprennent, sans que cette liste soit exhaustive, un ou plusieurs des brevets déposés aux États-Unis et indiqués à l'adresse http://www.sun.com/patents de même qu'un ou plusieurs brevets ou applications brevetées supplémentaires aux États-Unis et dans d'autres pays.

Ce document, le produit et les technologies afférents sont exclusivement distribués avec des licences qui en restreignent l'utilisation, la copie, la distribution et la décompilation. Aucune partie de ce produit, de ces technologies ou de ce document ne peut être reproduite sous quelque forme que ce soit, par quelque moyen que ce soit, sans l'autorisation écrite préalable de Fujitsu Limited et de Sun Microsystems, Inc., et de leurs éventuels bailleurs de licence. Ce document, bien qu'il vous ait été fourni, ne vous confère aucun droit et aucune licence, expresses ou tacites, concernant le produit ou la technologie auxquels il se rapporte. Par ailleurs, il ne contient ni ne représente aucun engagement, de quelque type que ce soit, de la part de Fujitsu Limited ou de Sun Microsystems, Inc., ou des sociétés affiliées.

Ce document, et le produit et les technologies qu'il décrit, peuvent inclure des droits de propriété intellectuelle de parties tierces protégés par copyright et/ou cédés sous licence par des fournisseurs à Fujitsu Limited et/ou Sun Microsystems, Inc., y compris des logiciels et des technologies relatives aux polices de caractères.

Par limites du GPL ou du LGPL, une copie du code source régi par le GPL ou LGPL, comme applicable, est sur demande vers la fin utilsateur disponible; veuillez contacter Fujitsu Limted ou Sun Microsystems, Inc.

Cette distribution peut comprendre des composants développés par des tierces parties.

Des parties de ce produit pourront être dérivées des systèmes Berkeley BSD licenciés par l'Université de Californie. UNIX est une marque déposée aux Etats-Unis et dans d'autres pays et licenciée exclusivement par X/Open Company, Ltd.

Sun, Sun Microsystems, le logo Sun, Java, Netra, Solaris, Sun StorEdge, docs.sun.com, OpenBoot, SunVTS, Sun Fire, SunSolve, CoolThreads, J2EE, et Sun sont des marques de fabrique ou des marques déposées de Sun Microsystems, Inc. aux Etats-Unis et dans d'autres pays.

Fujitsu et le logo Fujitsu sont des marques déposées de Fujitsu Limited.

Toutes les marques SPARC sont utilisées sous licence et sont des marques de fabrique ou des marques déposées de SPARC International, Inc. aux Etats-Unis et dans d'autres pays. Les produits portant les marques SPARC sont basés sur une architecture développée par Sun Microsystems, Inc.

SPARC64 est une marques déposée de SPARC International, Inc., utilisée sous le permis par Fujitsu Microelectronics, Inc. et Fujitsu Limited.

L'interface d'utilisation graphique OPEN LOOK et Sun™ a été développée par Sun Microsystems, Inc. pour ses utilisateurs et licenciés. Sun reconnaît les efforts de pionniers de Xerox pour la recherche et le développement du concept des interfaces d'utilisation visuelle ou graphique pour l'industrie de l'informatique. Sun détient une license non exclusive de Xerox sur l'interface d'utilisation graphique Xerox, cette licence couvrant également les licenciés de Sun qui mettent en place l'interface d'utilisation graphique OPEN LOOK et qui, en outre, se conforment aux licences écrites de Sun.

Droits du gouvernement américain - logiciel commercial. Les utilisateurs du gouvernement américain sont soumis aux contrats de licence standard de Sun Microsystems, Inc. et de Fujitsu Limited ainsi qu'aux clauses applicables stipulées dans le FAR et ses suppléments.

Avis de non-responsabilité: les seules garanties octroyées par Fujitsu Limited, Sun Microsystems, Inc. ou toute société affiliée de l'une ou l'autre entité en rapport avec ce document ou tout produit ou toute technologie décrit(e) dans les présentes correspondent aux garanties expressément stipulées dans le contrat de licence régissant le produit ou la technologie fourni(e). SAUF MENTION CONTRAIRE EXPRESSEMENT STIPULÉE DANS CE CONTRAT, FUJITSU LIMITED, SUN MICROSYSTEMS, INC. ET LES SOCIÉTÉS AFFILIÉES REJETTENT TOUTE REPRÉSENTATION OU TOUTE GARANTIE, QUELLE QU'EN SOIT LA NATURE (EXPRESSE OU IMPLICITE) CONCERNANT CE PRODUIT, CETTE TECHNOLOGIE OU CE DOCUMENT, LESQUELS SONT FOURNIS EN L'ÉTAT. EN OUTRE, TOUTES LES CONDITIONS, REPRÉSENTATIONS ET GARANTIES EXPRESSES OU TACITES, Y COMPRIS NOTAMMENT TOUTE GARANTIE IMPLICITE RELATIVE À LA QUALITÉ MARCHANDE, À L'APTITUDE À UNE UTILISATION PARTICULIÈRE OU À L'ABSENCE DE CONTREFAÇON, SONT EXCLUES, DANS LA MESURE AUTORISÉE PAR LA LOI APPLICABLE. Sauf mention contraire expressément stipulée dans ce contrat, dans la mesure autorisée par la loi applicable, en aucun cas Fujitsu Limited, Sun Microsystems, Inc. ou l'une de leurs filiales ne sauraient être tenues responsables envers une quelconque partie tierce, sous quelque théorie juridique que ce soit, de tout manque à gagner ou de perte de profit, de problèmes d'utilisation ou de perte de données, ou d'interruptions d'activités, ou de tout dommage indirect, spécial, secondaire ou consécutif, même si ces entités ont été préalablement informées d'une telle éventualité.

LA DOCUMENTATION EST FOURNIE "EN L'ETAT" ET TOUTES AUTRES CONDITIONS, DECLARATIONS ET GARANTIES EXPRESSES OU TACITES SONT FORMELLEMENT EXCLUES, DANS LA MESURE AUTORISEE PAR LA LOI APPLICABLE, Y COMPRIS NOTAMMENT TOUTE GARANTIE IMPLICITE RELATIVE A LA QUALITE MARCHANDE, A L'APTITUDE A UNE UTILISATION PARTICULIERE OU A L'ABSENCE DE CONTREFACON.

### Contents

Preface vii SPARC Enterprise T2000 Server Features 2 Features at a Glance 3 Chip-Multitheaded Multicore Processor and Memory Technology 5 Performance Enhancements 6 PreInstalled Solaris Operating System 6 Preloaded Java Enterprise System Software 7 Hardware-Assisted Cryptography 8 Remote Manageability With ALOM CMT 8 System Reliability, Availability, and Serviceability 9 Hot-Swappable Components 9 Power Supply Redundancy 9 Fan Redundancy 10 Environmental Monitoring 10 Support for RAID Storage Configurations 10 Error Correction and Parity Checking 11 Fault Management and Predictive Self Healing 11 Rackmountable Enclosure 11 Chassis Identification 12

## Preface

This document describes the hardware and software features, options, and specifications for the SPARC Enterprise T2000 server.

## FOR SAFE OPERATION

This manual contains important information regarding the use and handling of this product. Read this manual thoroughly. Use the product according to the instructions and information available in this manual. Keep this manual handy for further reference. Fujitsu makes every effort to prevent users and bystanders from being injured or from suffering damage to their property. Use the product according to this manual.

# **Related Documentation**

The latest versions of all the SPARC Enterprise Series manuals are available at the following Web sites:

Global Site

http://www.fujitsu.com/sparcenterprise/manual/

Japanese Site

http://primeserver.fujitsu.com/sparcenterprise/manual/

Title	Description	Manual Code
SPARC Enterprise T2000 Server Product Notes	Information about the latest product updates and issues	C120-E374
SPARC Enterprise T2000 Server Site Planning Guide	Server specifications for site planning	C120-H017
SPARC Enterprise T2000 Server Getting Started Guide	Information about where to find documentation to get your system installed and running quickly	C120-E372
SPARC Enterprise T2000 Server Installation Guide	Detailed rackmounting, cabling, power on, and configuring information	C120-E376
SPARC Enterprise T2000 Server Service Manual	How to run diagnostics to troubleshoot the server, and how to remove and replace parts in the server	C120-E377
SPARC Enterprise T2000 Server Administration Guide	How to perform administrative tasks that are specific to this server	C120-E378
Advanced Lights out Management (ALOM) CMT v1.x Guide	How to use the Advanced Lights Out Manager (ALOM) software	C120-E386
SPARC Enterprise T2000 Server Safety and Compliance Guide	Safety and compliance information about this server	C120-E375

**Note** – Product Notes is available on the website only. Please check for the recent update on your product.

- Manuals included on the Enhanced Support Facility CD-ROM disk
  - Remote maintenance service

Title	Manual Code
Enhanced Support Facility User's Guide for REMCS	C112-B067

Solaris Operating System-Related Manuals

http://docs.sun.com

# Conventions for Alert Messages

This manual uses the following conventions to show alert messages, which are intended to prevent injury to the user or bystanders as well as property damage, and important messages that are useful to the user.



**Warning** – This indicates a hazardous situation that could result in death or serious personal injury (potential hazard) if the user does not perform the procedure correctly



**Caution** – This indicates a hazardous situation that could result in minor or moderate personal injury if the user does not perform the procedure correctly. This signal also indicates that damage to the product or other property may occur if the user does not perform the procedure correctly.

## Alert messages in the text

An alert message in the text consists of a signal indicating an alert level followed by an alert statement. Alert messages are indented to distinguish them from regular text. Also, a space of one line precedes and follows an alert statement.



**Caution** – The following tasks regarding this product and the optional products provided from Fujitsu should only be performed by a certified service engineer. Users must not perform these tasks. Incorrect operation of these tasks may cause malfunction.

Unpacking optional adapters and such packages delivered to the users

# Product Handling

#### Maintenance



**Warning** – Certain tasks in this manual should only be performed by a certified service engineer. User must not perform these tasks. Incorrect operation of these tasks may cause electric shock, injury, or fire.

- Installation and reinstallation of all components, and initial settings
- Removal of front, rear, or side covers
- Mounting/de-mounting of optional internal devices
- Plugging or unplugging of external interface cards
- Maintenance and inspections (repairing, and regular diagnosis and maintenance)

**Caution** – The following tasks regarding this product and the optional products provided from Fujitsu should only be performed by a certified service engineer. Users must not perform these tasks. Incorrect operation of these tasks may cause malfunction.

- Unpacking optional adapters and such packages delivered to the users
- Plugging or unplugging of external interface cards

## Remodeling/Rebuilding

**Caution** – Do not make mechanical or electrical modifications to the equipment. Using this product after modifying or reproducing by overhaul may cause unexpected injury or damage to the property of the user or bystanders.



# Fujitsu Welcomes Your Comments

We would appreciate your comments and suggestions to improve this document. You can submit your comments by using "Reader's Comment Form"

#### Reader's Comment Form

We would appreciate your comments and suggestions for improving this publication.

Date:	Publication No.:
Your Name:	Publication Name:
Company:	_
Address:	
City/State/Zip:	_
Phone/Email address:	-

Your Comments:

Page	Line	Comments		
	Reply requested: o Yes o No			

Please evaluate the overall quality of this manual by checking (  $\checkmark$  )the appropriate boxes

	Good	Fair	Poor	Go	ood	Fair	Poor	Go	od F	'air l	Poor
Organization:	0	0	0	Use of examples:	0	0	0	Legibility:	0	0	0
Accuracy:	0	0	0	Index coverage:	0	0	0	Binding:	0	0	0
Clarity:	0	0	0	Cross				Figures and tables:	0	0	0
Overall rating of				referencing:	0	0	0	General appearance:	0	0	0
this publication:	0	0	0								
Technical level:	0 1	`oo d	letailed	o Appropriate		0	Not en	ough detail			

All comments and suggestions become the property of Fujitsu Limited.

## For Users in U.S.A., Canada, and Mexico

Fold and fasten as shown on back No postage necessary if mailed in U.S.A.

Fujitsu Computer Systems Attention: Engineering Ops M/S 249 1250 East Arques Avenue P.O. Box 3470 Sunnyvale, CA 94088-3470 FAX: (408) 746-6813

#### For Users in Other Countries

Fax this form to the number below or send this form to the address below.

Fujitsu Learning Media Limited FAX: 81-3-3730-3702 37-10 Nishi-Kamata 7-chome Oota-Ku Tokyo 144-0051 JAPAN

#### FUJITSU LIMITED



Ildudulluduldulduldulludullud

FOLD AND TAPE

\_ \_ \_ \_ \_ \_ \_ \_

\_ \_ \_ \_ \_ \_

## SPARC Enterprise T2000 Server Features

This chapter describes the features of the SPARC Enterprise T2000 server. The following topics are covered:

- "SPARC Enterprise T2000 Server Features" on page 2
- "Features at a Glance" on page 3
- "Chassis Identification" on page 12

# SPARC Enterprise T2000 Server Features

The SPARC Enterprise T2000 server is a scalable and reliable high-performance, entry-level server, offering the following characteristics:

- Space efficient, rack-optimized 2U form factor for horizontally scaled environments.
- Chip multithreading technology (CMT) in the UltraSPARC<sup>®</sup> T1 processor with CoolThreads<sup>TM</sup> technology offering four or eight cores, with four threads per core for improved throughput and reduced power consumption.
- Four on-board Ethernet ports providing efficient integration and connectivity.

Investment protection with SPARC® V9 binary application compatibility and the Solaris<sup>™</sup> 10 Operating System. The Solaris 10 OS also provides features such as Solaris Predictive Self-Healing, Solaris Dynamic Tracing, and support across UltraSPARC platforms.



FIGURE 1 SPARC Enterprise T2000 Server

## Features at a Glance

Feature	Description
Processor	1 UltraSPARC T1 multicore processor (4 or 8 cores)
Architecture	SPARC V9 architecture, ECC protected Platform group: sun4v Platform name: SUNW,SPARC-Enterprise-T2000
Memory	<ul> <li>16 slots that can be populated with one of the following types of DDR-2, 400 MHz DIMMS with ECC:</li> <li>512 MB (8 GB maximum)</li> <li>1 GB (16 GB maximum)</li> <li>2 GB (32 GB maximum)</li> <li>4GB (64 GB maximum)</li> </ul>
Ethernet ports	4 ports, 10/100/1000 Mb autonegotiating
Internal hard drives	1-4 SFF SAS 73 GB, 10k rpm, 2.5-inch form factor drives (hot pluggable)
Other internal peripherals	1 slimline DVD-R/CD-RW device
USB ports	4 USB 1.1 ports (2 in front and 2 in rear)
Cooling	3 hot-swappable and redundant system fans and 1 blower unit
PCI interfaces	<ul> <li>3 PCI Express slots that support<sup>*</sup> cards with the following specifications:</li> <li>low-profile</li> <li>x1, x4, and x8 width</li> <li>12v and 3.3v as defined by the PCI Express specification</li> </ul>
	<ul> <li>2 PCI-X slots that support* cards with the following specifications:</li> <li>64-bit, 133 MHz</li> <li>low-profile</li> <li>3.3v (5v is also supplied, as defined by the PCI-X specification, using a 3.3V form factor connector)</li> </ul>
Power	2 hot-swappable and redundant power supply units (PSUs) Refer to the <i>SPARC Enterprise T2000 Server Site Planning Guide</i> for power and environmental specifications.
Remote management	ALOM CMT management controller with a serial and 10/100 Mb Ethernet port

 TABLE 1
 SPARC Enterprise T2000 Server Features at a Glance

TABLE 1	SPARC Enterp	rise T2000	Server	Features	at a Glance
---------	--------------	------------	--------	----------	-------------

Feature	Description		
Firmware	<ul><li>System Firmware comprising:</li><li>OBP for system settings and power-on self test (POST) support</li><li>ALOM CMT for remote management administration</li></ul>		
Cryptography	Hardware-assisted cyptographic acceleration		
Operating system	Solaris <sup>™</sup> 10 Operating System preinstalled on disk 0 Refer to the <i>SPARC Enterprise T2000 Server Product Notes</i> for information on the minimum version of supported OS and required patches.		
Other software	Java <sup>™</sup> Enterprise System with a 90-day trial licence		
Other	This server complies with the Restriction of Hazardous Substances (RoHS) directive 2002/95/EC.H. Refer to the <i>SPARC Enterprise T2000 Server Installation Guide</i> for certification information.		

\* PCI-E and PCI-X specifications described in this table list the physical requirements for PCI cards. Additional support capabilities must also be provided (such as device drivers) for a PCI card to function in the server. Refer to the specifications and documentation for a given PCI card to determine if the required drivers are provided that enable the card to function in this server.

Refer to the *SPARC Enterprise T2000 Server Service Manual* for hardware configuration information. Refer to the *SPARC Enterprise T2000 Server Administration Guide* for administrative tasks that are specific to this server.

## Chip-Multitheaded Multicore Processor and Memory Technology

The UltraSPARC<sup>®</sup> T1 multicore processor is the basis of the SPARC Enterprise T2000 server. The UltraSPARC T1 processor is based on chip multithreading (CMT) technology that is optimized for highly threaded transactional processing. The UltraSPARC T1 processor improves throughput while using less power and dissipating less heat than conventional processor designs.

Depending on the model purchased, the processor has four or eight UltraSPARC cores. Each core equates to a 64-bit execution pipeline capable of running four threads. The result is that the 8-core processor handles up to 32 active threads concurrently.

Additional processor components, such as L1 cache, L2 cache, memory access crossbar, DDR2 memory controllers, and a JBus I/O interface have been carefully tuned for optimal performance. See FIGURE 2.



FIGURE 2 UltraSPARC T1 Multicore Processor Block Diagram

#### Performance Enhancements

The SPARC Enterprise T2000 server running the Solaris 10 OS provides several new performance enhancing technologies with its sun4v architecture and multicore multithreaded UltraSPARC T1 multicore processor.

Some of these enhancements are:

- Large page optimization
- Reduction on TLB misses
- Optimized block copy
- Improved web services performance through the kernel-level SSL proxy Solaris 10 OS feature

#### PreInstalled Solaris Operating System

The SPARC Enterprise T2000 server is preinstalled with the Solaris 10 OS, and offers the following Solaris OS features:

- Stability, high performance, scalability, and precision of a mature 64-bit operating system
- Support for over 12,000 leading technical and business applications
- Solaris Containers Isolate software applications and services using flexible, software-defined boundaries.
- DTrace A comprehensive dynamic tracing framework for tuning applications and troubleshooting systemic problems in real time.
- Predictive Self-Healing Capability that automatically diagnoses, isolates, and recovers from many hardware and application faults.
- Security Advanced security features designed to protect the enterprise at multiple levels.
- Network Performance Completely rewritten TCP/IP stack dramatically improves the performance and scalability of your networked services.

If you prefer to install the Solaris OS rather then use the preinstalled Solaris OS, you can do so. The SPARC Enterprise T2000 server supports Solaris 10 OS. For possible updates to supported Solaris releases, refer to the *SPARC Enterprise T2000 Server Product Notes*.

## Preloaded Java Enterprise System Software

The SPARC Enterprise T2000 server is preinstalled with Java<sup>™</sup> Enterprise System software and includes a free 90-day evaluation license for the following Java Enterprise System software applications:

- Access Manager A security foundation that helps manage secure access to an enterprises' web applications by offering single sign-on (SSO) as well as enabling federation across trusted networks.
- Application Server Provides a Java 2 Platform, Enterprise Edition (J2EE platform) 1.4 compatible platform for developing and delivering server-side Java applications and web services.
- Calendar Server A Web-based tool that facilitates team collaboration by enabling users to manage and coordinate appointments, events, tasks, and resources.
- Cluster software Delivers high availability to enterprise system applications.
- Directory Server User-management infrastructure for enterprises that manage high volumes of user information by providing a centralized repository for storing and managing user profiles and access privileges, as well as application and network resource information.
- Directory Proxy Server Provides secure firewall-like services for the Directory Server.
- Instant Messaging A standards-based, real-time communication and collaboration application.
- Message Queue An enterprise-level message server using a standards-based (JMS) messaging solution.
- Messaging Server A high-performance, highly secure messaging platform that provides security features that help ensure the integrity of communications.
- Portal Server Provides portal services that identify users through centralized identity services using roles, and policies.
- Web Server A secure, reliable, easy-to-use web server designed for medium and large business applications.

To gain the benefits of the Java Enterprise System, you can buy a subscription license for a Java Enterprise System Suite, or a combination of Java System Suites.

## Hardware-Assisted Cryptography

The UltraSPARC T1 multicore processor provides hardware-assisted acceleration of RSA and DSA cryptographic operations. The Solaris 10 Operating System provides the multithreaded device driver (ncp device driver) that supports the hardware-assisted cryptography.

#### Remote Manageability With ALOM CMT

The Advanced Lights Out Management (ALOM CMT) feature is a system controller that enables you to remotely manage and administer the SPARC Enterprise T2000 server.

The ALOM CMT software is preinstalled as firmware, and initializes as soon as you apply power to the system. You can customize ALOM CMT to work with your particular installation.

ALOM CMT enables you to monitor and control your server over a network, or by using a dedicated serial port for connection to a terminal or terminal server. ALOM CMT provides a command-line interface that you can use to remotely administer geographically distributed or physically inaccessible machines. In addition, ALOM CMT enables you to run diagnostics (such as POST) remotely that would otherwise require physical proximity to the server's serial port.

You can configure ALOM CMT to send email alerts of hardware failures, hardware warnings, and other events related to the server or to ALOM CMT. The ALOM CMT circuitry runs independently of the server, using the server's standby power. Therefore, ALOM CMT firmware and software continue to function when the server operating system goes offline or when the server is powered off. ALOM CMT monitors the following SPARC Enterprise T2000 server components:

- CPU temperature conditions
- Disk drive status
- Enclosure thermal conditions
- Fan speed and status
- Power supply status
- Voltage conditions

For information about configuring and using the ALOM system controller, refer to the *Advanced Lights Out Management (ALOM) CMT Guide*.

## System Reliability, Availability, and Serviceability

Reliability, availability, and serviceability (RAS) are aspects of a system's design that affect its ability to operate continuously and to minimize the time necessary to service the system. Reliability refers to a system's ability to operate continuously without failures and to maintain data integrity. System availability refers to the ability of a system to recover to an operational state after a failure, with minimal impact. Serviceability relates to the time it takes to restore a system to service following a system failure. Together, reliability, availability, and serviceability features provide for near continuous system operation.

To deliver high levels of reliability, availability, and serviceability, the SPARC Enterprise T2000 server offers the following features:

- Hot-swappable hard drives
- Redundant, hot-swappable power supplies (two)
- Redundant hot-swappable fan units (three) and one blower unit
- Environmental monitoring
- Internal hardware drive mirroring (RAID 1)
- Error detection and correction for improved data integrity
- Easy access for most component replacements

For more information about using RAS features, refer to the *SPARC Enterprise* T2000 *Server Administration Guide*.

#### Hot-Swappable Components

SPARC Enterprise T2000 server hardware is designed to support hot-swapping of the chassis-mounted hard drives, fan units, and power supplies. By using the proper software commands, you can install or remove these components while the system is running. Hot-swap technology significantly increases the system's serviceability and availability by providing the ability to replace hard drives, fan units, and power supplies without service disruption.

#### Power Supply Redundancy

The SPARC Enterprise T2000 server features two hot-swappable power supplies, enabling the system to continue operating should one of the power supplies fail or if one power source fails.

The SPARC Enterprise T2000 server also has a single hot-swappable blower unit that works in conjunction with the power supply fans to provide cooling for the internal disk drives. If the blower unit fails, the three functioning fan units provide enough cooling to keep the system running.

#### Fan Redundancy

The SPARC Enterprise T2000 server features three hot-swappable system fans. The fans enable the system to continue operating with adequate cooling in the event that one of the fans fails.

#### **Environmental Monitoring**

The SPARC Enterprise T2000 server features an environmental monitoring subsystem protects the server and its components against:

- Extreme temperatures
- Lack of adequate airflow through the system
- Power supply failures
- Hardware faults

Temperature sensors are located throughout the system to monitor the ambient temperature of the system and internal components. The software and hardware ensure that the temperatures within the enclosure do not exceed predetermined safe operation ranges. If the temperature observed by a sensor falls below a lowtemperature threshold or rises above a high-temperature threshold, the monitoring subsystem software lights the amber Service Required LEDs on the front and back panel. If the temperature condition persists and reaches a critical threshold, the system initiates a graceful system shutdown. In the event of a failure of the system controller, backup sensors protect the system from serious damage, by initiating a forced hardware shutdown.

All error and warning messages are logged in the ALOM CMT event log and are optionally sent to the system controller (SC) system console. Service Required LEDs remain lit after an automatic system shutdown to aid in problem diagnosis.

The power subsystem is monitored in a similar fashion by monitoring power supplies and reporting any fault in the front and rear panel LEDs.

If a power supply problem is detected, an error message is logged in the ALOM CMT event log and optionally sent to the SC system console. Additionally, LEDs located on each power supply light to indicate failures. The system Service Required LED lights to indicate a system fault.

#### Support for RAID Storage Configurations

You can set up a hardware RAID 1 (mirroring) and hardware RAID 0 (striping) configurations for any pair of internal hard drives, providing a high-performance solution for hard drive mirroring.

By attaching one or more external storage devices to the SPARC Enterprise T2000 server, you can use a redundant array of independent drives (RAID) software application such as Solstice DiskSuite<sup>™</sup> or VERITAS Volume Manager to configure system drive storage in a variety of different RAID levels.

#### Error Correction and Parity Checking

The UltraSPARC T1 multicore processor provides parity protection on its internal cache memories, including tag parity and data parity on the D-cache and I-cache. The internal 3MB L2 cache has parity protection on the tags, and ECC protection on the data.

Advanced ECC, also called chipkill, corrects up to 4-bits in error on nibble boundaries, as long as they are all in the same DRAM. If a DRAM fails, the DIMM continues to function.

#### Fault Management and Predictive Self Healing

The SPARC Enterprise T2000 server features the latest fault management technologies. The Solaris 10 OS architecture provides a means for building and deploying systems and services capable of *predictive self-healing*. Self-healing technology enables systems to accurately predict component failures and mitigate many serious problems before they actually occur. This technology is incorporated into both the hardware and software of the SPARC Enterprise T2000 server.

At the heart of the predictive self-healing capabilities is the Solaris Fault Manager, a new service that receives data relating to hardware and software errors, and automatically and silently diagnoses the underlying problem. Once a problem is diagnosed, a set of agents automatically responds by logging the event, and if necessary, takes the faulty component offline. By automatically diagnosing problems, business-critical applications and essential system services can continue uninterrupted in the event of software failures, or major hardware component failures.

## Rackmountable Enclosure

The SPARC Enterprise T2000 server uses a space-saving 2U-high rackmountable enclosure that can be installed into a variety of industry standard racks.

# Chassis Identification

The following figures show the physical characteristics of the SPARC Enterprise T2000 server.



FIGURE 3 SPARC Enterprise T2000 Server Front Panel



FIGURE 4 SPARC Enterprise T2000 Server Rear Panel

For details on how to install the server refer to the SPARC Enterprise T2000 Server Installation Guide.

