

This Customer Design Review Supplement is provided to prevent problems that may arise in the system development of MB96340 series.  
A complete system may not always be configured even if the following items are completely satisfied, but confirm at least the following items.  
We will recommend this Customer Design Review Supplement used to be filed as a review results.

Item		Check	Reason for checking	Result	Remark	Update
CPU	Watchdog	Is the watchdog timer cleared by, for example, a timer interrupt? (Are incorrect PLL multiplication settings considered?)	When the watchdog reset interval is not sufficient, whether a program is proceeding normally cannot be detected.	Yes / No		2007/11/27
CPU	External reset IC	When using external reset IC, is the low-voltage detecting value within the guaranteed operation voltages of the microcomputer? Is the voltage drop between detection and reset considered?	When no reset within the guaranteed operation voltages is entered, a malfunction may occur.	Yes / No	Confirm the guaranteed operation voltage range in the data sheet.	2007/11/27
CPU	External reset	Does the reset range meet the Fujitsu's standard?	When the reset range does not meet the Fujitsu's standard, recovery cannot be implemented.	Yes / No		2007/11/27
CPU	Power-on reset	Is the standard on electrical characteristics concerning power-on reset being met?	Powering on without meeting the power-on reset standard may result in the execution of commands by CPU without the power-on reset implemented normally.	Yes / No	Applied to systems using reset at power-on (Not applied to systems using power monitoring IC for reset equivalent input).	2007/11/27
CPU	Reset cause bits	When using the Reset Cause and Clock status (RCCSR/RCCSRC) register's reset cause bits, is the RCCSRC register read once by using the program default setting, followed by the clearing of the reset cause bits?	The default values of all reset cause bits are undefined. Accordingly, in order to clear all reset cause bits, ensure that the RCCSRC register is read once before using it.	Yes / No	Applied only when reset cause bits are used.	2007/11/27
CPU	Subclock oscillation stabilization wait	Has the state transition from the main mode to the subclock mode taken place while the subclock oscillation is still unstable?	The subclock needs longer oscillation stabilization time than the main clock does. Thus, before the state transition to the subclock mode takes place, oscillation of the subclock needs to stabilize.	Yes / No	Only when the subclock is used	2007/11/27
CPU	Main clock oscillation stabilization wait	Is the required oscillation stabilization wait time identified by obtaining matching data of the system and oscillator?	CPU may be run before oscillation has stabilized.	Yes / No	Make a request of the oscillation evaluation to the manufacturer of the oscillator to be used.	2007/11/27
Peripheral	A/D converter	Is analog impedance the analog impedance described in the datasheet or less. When the analog impedance is higher, it is required to set the sample hold time longer or install an external capacitor of approximate 0.1 uF.	When the analog impedance is higher, the sampling time of analog data may become shorter than required time.	Yes / No	Only when A/D converter is used.	2007/11/27
Peripheral	A/D converter	Is voltages of AVR and AVCC are sufficiently stable?	To separate power supplies of analog system and digital system, a reactance device may be mounted in AVR and AVCC. In this case, it is recommended to configure the circuit by adding a capacitor of some micro F so that sufficient power is supplied at A/D start.	Yes / No	Only when A/D converter is used.	2007/11/27
Peripheral	A/D converter	Is analog sampling time sufficiently long?	When analog input impedance is larger, a glitch may occur at analog input pin. The glitch is determined by the analog impedance and time constant of internal capacitance. When sample hold time is shorter, sample hold value may be affected by the glitch. Because the influence of the glitch is different between FLASH product and MASK product, it is recommended to set a sufficient sample hold time when the analog input impedance is larger.	Yes / No	Only when the analog input impedance used is larger than the analog input impedance recommended by the Data Sheet.	2007/11/27
Peripheral	A/D converter	Are the completion and start of A/D conversion implemented at the same time?	When the completion and start of A/D conversion are implemented at the same time, the later operation, the start of the A/D conversion, may be ignored.	Yes / No	Only when A/D conversion is started during A/D conversion performed.	2007/11/27
Peripheral	A/D converter	Is the analog input enable register(ADER) set to port input mode, when A/D converter is used?	When the port input mode is set with the ADER and A/D input (voltage of medium potential) is implemented, through current flows in CMOS input circuit of I/O port and the current consumption is increased.	Yes / No	Only when A/D converter is used.	2007/11/27
Peripheral	A/D converter	When the consecutive ADC operation is paused by the data protection function, is the interrupt is cleared?	Normal A/D operation cannot occur.	Yes / No	Refer to "ADC Interrupt error".	2007/11/27
Peripheral	Interrupt	Is the interrupt vector processing of an exceptional interrupt performed?	Runaway may be caused when an undefined instruction is executed due, for example, to runaway.	Yes / No	When an undefined instruction is executed, an exceptional interrupt occurs. Thus, when special processing is needed, jump to the processing. When no special processing is needed, jumping to a reset vector is recommended.	2007/11/27
Peripheral	Interrupt	Is processing of an unused interrupt vector performed?	Runaway may be caused when an unused interrupt occurs due, for example, to runaway.	Yes / No	When special processing is needed, jump to the processing. When no special processing is needed, jumping to a reset vector is recommended.	2007/11/27
Peripheral	I/O port	Is processing such as additional writing performed for the purpose of a fail-safe system in important port input/output?	Basically, the port state does not change as long as not set by software. However, for the purpose of making the system fail-safe, it is recommended to insert software of a refresh function such as additional writing into important ports.	Yes / No		2007/11/27

This Customer Design Review Supplement is provided to prevent problems that may arise in the system development of MB96340 series.  
 A complete system may not always be configured even if the following items are completely satisfied, but confirm at least the following items.  
 We will recommend this Customer Design Review Supplement used to be filed as a review results.

Item		Check	Reason for checking	Result	Remark	Update
Peripheral	I/O port	When using the CMOS I/O port for output, is the DDRx register set after setting the PDRx register?	Since the initial value of the PDRx register is undefined, if the DDRx register is set for output without setting the PDRx register, the output becomes undefined. Before setting the DDRx register for output, set the PDRx register first.	Yes / No		2007/11/27
Peripheral	Flash	Do you know that FLASH memory cannot be read while writing to/deleting (chip deletion/sector deletion) FLASH memory?	While writing to/deleting (chip deletion/sector deletion) FLASH memory, no interrupt vector on FLASH memory cannot be read, either. Thus, remember that no interrupt processing can be performed while writing/deleting.	Yes / No	Only when FLASH memory is written by the user	2007/11/27
Peripheral	Flash	When users are allowed to write to FLASH memory in user programming mode, is the hardware sequence flag used to control writing to FLASH memory?	Since the FMCS register cannot be used to check for write/delete errors, it is recommended to use the hardware sequence flag to control writing to/deleting FLASH memory.	Yes / No	Only when FLASH memory is written to by the user	2007/11/27
Others	General	Do the voltage, ambient temperature, and operating frequency ranges satisfy the standards specified by Fujitsu? When any of them does not satisfy the standards, is any special guarantee considered and supported?	When not used within the guarantee range, no product guarantee can be provided.	Yes / No	Check the guaranteed operation range in the data sheet.	2007/11/27
Others	General	When a special guarantee is considered, is a notification form returned to the Sales Dept. after affixing a "confirmation stamp ((No problem, Problem found) in the reply)" on the notification form?	If a special guarantee is provided, test changes may be needed. Thus, make sure to return the notification form before ROM release.	Yes / No	Since it may take up to several months to deal with test changes, they may not be dealt with when the notification form is returned just before ROM release.	2007/11/27
Noise reduction measures and others	Oscillation	Is oscillation matching data of mass-produced products obtained?	Since oscillation characteristics of flash products and those of mask products may be different, it is recommended to obtain oscillation matching data of mass-produced products.	Yes / No	Make a request of the oscillation evaluation to the manufacturer of the oscillator to be used.	2007/11/27
Noise reduction measures and others	Mode(MD) pin	Is interconnect for treating the MOD pin too long or is there any adjacent high current signal interconnect?	The level of the MOD pin may be read incorrectly due to power supply deviation and noise.	Yes / No		2007/11/27
Noise reduction measures and others	Oscillation	When using a crystal oscillator, is an appropriate dumping resistor inserted?	To use a crystal oscillator, a dumping resistor to reduce the excitation current is needed.	Yes / No	Make a request of the oscillation evaluation to the manufacturer of the oscillator to be used.	2007/11/27
Noise reduction measures and others	Oscillation	Is the resistance of the dumping resistor for the oscillation circuit determined in view of unnecessary radiation noise and oscillation amplitude?	When oscillation is abnormal or an overshoot or undershoot of oscillation occurs, unnecessary radiation noise may increase.	Yes / No	When a problem of unnecessary radiation noise arises, it is necessary to first confirm the oscillation waveforms and then examine whether to insert a dumping resistor as a measure to reduce unnecessary radiation noise.	2007/11/27
Noise reduction measures and others	Oscillation	Is the oscillator arranged as close to the chip as possible?	CPU runaway due to external noise may be presumed.	Yes / No	It is recommended to arrange the oscillator as close to the chip as possible?	2007/11/27
Noise reduction measures and others	Vcc, GND	Is consideration given to making Vcc and GND as strong as possible?	Problems of unnecessary radiation noise and CPU runaway due to external noise may be presumed.	Yes / No	To avoid problems of unnecessary radiation noise and external noise, it is recommended to take the power supply and GND as widely as possible (By arranging GND under the chip, for example, the GND can be strengthened).	2007/11/27
Peripheral	Unused pin treatment	Is any unused pin pulled up or pulled down by the resistor of 2 k or more? Or, is the port output treatment performed in the initial routine by leaving the pin opened?	When an unused pin is treated without a resistor and the port level opposite to the processing level is output due to CPU runaway, problems such as latch-up may arise.	Yes / No		2007/11/27
Noise reduction measures and others	Capacitor	Is the optimum capacitor connected near the chips as a capacitor for reducing noise?	The capacitor connected to reduce noise may not work with reactance components of interconnect (Measures that take noise components into account are needed).	Yes / No		2007/11/27
Noise reduction measures and others	C pin	The capacitance of the smoothing capacitor connected to Vcc is larger than that of the capacitor connected to C pin?	When the capacitance of the smoothing capacitor is smaller, the internal regulator may become unstable.	Yes / No		2007/11/27
Noise reduction measures and others	Software	Is the setting made in which Start.asm is linked at first at the development with C language?	In Start.asm of Softune, the link is generated automatically at the beginning of the address where RAM is cleared. Therefore, when Start.asm is used, it is necessary to set the order of the link at first because the address information becomes wrong if it is not set.	Yes / No	Only for the use of Start.asm of Softune.	2007/11/27

This Customer Design Review Supplement is provided to prevent problems that may arise in the system development of MB96340 series.  
 A complete system may not always be configured even if the following items are completely satisfied, but confirm at least the following items.  
 We will recommend this Customer Design Review Supplement used to be filed as a review results.

Item		Check	Reason for checking	Result	Remark	Update
Noise reduction measures and others	ESD, latch-up, noise	Are mass-produced chips used to evaluate ESD, latch-up, and noise resistances?	Since the resistances against ESD, latch-up, and noise of Flash products and those of mask products are different, it is recommended to use mass-produced products to evaluate ESD and latch-up resistance.	Yes / No	Since it is possible to submit measurement results of Fujitsu as characteristic examples of resistance characteristic data between MASK and FLASH products, make a request of them.	2007/11/27
Noise reduction measures and others	Connection of reactance	Is reactance connected directly with power supply?	The characteristic of internal regulator might not be obtained by the reactance element.	Yes / No	If reactance is put directly in the power supply of chip, it is necessary to connect capacitor between chip power supply and reactance.	2007/11/27
Noise reduction measures and others	Memory map	Are the operation checks made by enabling the guarded break for unused area conforming to the ROM and RAM amounts of the Flash and mask chips in the memory map for tool evaluation?	The built-in memory amount of the EVA chip for evaluation and that of the Flash and mask chip are different. Therefore, the actual chips may not work even if normal operation is confirmed by using a tool.	Yes / No		2007/11/27
Noise reduction measures and others	Bit manipulation instruction	Read-modify instruction is prohibited by some registers of each resource. Is any RMW instruction used in the target register?(Is not RMW instruction executed for the register including write only bit?)	The instruction may not be executed normally, resulting in unintended data being written. Since, when a read-modify-write related instruction (such as SETB) is used on a register with write-only bits, the read value of the write-only bit is undefined, problems may be caused (When safety use of the read-modify-write instructions is described in the manual for a register, no problem will be caused).	Yes / No	Read-modify-write related instruction is indicated in the instruction list by * in RMW.	2007/11/27
Noise reduction measures and others	Stack usage	Is the maximum usage of stack confirmed?	Incorrect estimation of the stack usage could lead to RAM damage.	Yes / No	It is recommended to use the C analyzer of Softune to confirm the maximum usage of stack (Since the C analyzer cannot confirm a dynamic stack, it is necessary to consider the possibility of multiple interrupts when confirming the maximum usage).	2007/11/27
Noise reduction measures and others	Operation mode of tools	Is the operation confirmed by setting the operation mode to the native mode for final tool evaluation?	The native mode and debug mode are available as the operation modes of tools. Since the working speed in debug mode is different from the actual working speed, it is recommended to make an evaluation after setting the native mode.	Yes / No		2007/11/27