LifeBook C2320

- Brilliant SuperFine LCD display for excellent movie viewing and rich multimedia playback
- Designed for Microsoft® Windows® operating systems
- 2MB L2 Cache for faster access to your most frequented applications
- Multi interfaces for accessories connections USB 2.0, SD, Memory Stick PRO, CF, PC Card and IEEE1394
- The ideal desktop replacement notebook for home and office

Fujitsu recommends Microsoft® Windows® XP Professional for Mobile Computing.



		4
	C2320 Recommended Configurations	
Platform	Intel® Centrino™ Mobile Technology	Intel [®] Centrino™ Mobile Technology
	- Intel® Pentium® M Processor 735	- Intel® Pentium® M Processor 715
	(1.70GHz, 2MB L2 Cache, 400MHz FSB)	(1.50GHz, 2MB L2 Cache, 400MHz FSB)
	- Intel® PRO/Wireless 2200BG network connection	- Intel® PRO/Wireless 2200BG network connection
	- Intel [®] 855GM Chipset	- Intel® 855GM Chipset
OS Supported	Microsoft® Windows® XP Home Edition	
	Microsoft® Windows® XP Professional Edition	
	Microsoft® Windows® 2000 Professional Edition	
Display	15" SuperFine XGA TFT, 1024 x 768 pixels	15" SuperFine XGA TFT, 1024 x 768 pixels
Modular Bay Drive	DVD Super Multi Drive	DVD/CD-RW Combo Drive
Memory	512MB DDR266 (256MB on Board)	256MB DDR266 on Board
Hard Disk	60GB	40GB
Battery	Up to 2.7hrs ¹ (4-Cell 2000mAh)	
Weight	3.5kg	
	Specifications	
Maximum Memory Supported	1280MB DDR266, 1 DDR DIMM slot	
Hard Disk Drive	Ultra DMA/100 and S.M.A.R.T support	
Graphics	Integrated Intel® Extreme Graphics 2 with DVMT² delivers low-power, high-performance 2D/3D graphics, video,	
	and display capabilities at a maximum shared memory of 64MB	
Audio	SigmaTel STAC9751T codec with built-in Stereo Speakers	
Communication	56K V.92 ³ modem, IrDA 1.1 4Mbps ⁵ , 100/10Mbps ⁴ Fast Ethernet and Intel [®] PRO/Wireless 2200BG network	
	connection 802,11b/g with Dual Antenna. Separate ON/OFF switch for wireless network connection	
User Interface	Keyboard: 82-key, 19mm key pitch, 3mm key stroke	

SigmaTel STAC9751T codec with built-in Stereo Speakers	
56K V.92³ modem, IrDA 1.1 4Mbps⁵, 100/10Mbps⁴ Fast Ethernet and Intel® PRO/Wireless 2200BG network	
connection 802,11b/g with Dual Antenna. Separate ON/OFF switch for wireless network connection	
Keyboard: 82-key, 19mm key pitch, 3mm key stroke	
Touch Pad with Scroll Button	
Built-in 1.44MB FDD	
PC Card Type I/II x 2 / Type III x 1	
SD Card / Memory Stick PRO x1	
USB 2.0 x 4, VGA (external display), RJ45 (LAN), RJ11 (modem), IEEE1394, Headphone-out, Microphone-in, S-Video	
terminal, Serial, Parallel, Power Adapter AC-in	
Four programmable application launch buttons (Internet, Email and two other software)	
329mm (W) x 285.5mm (D) x 45.2mm <i>min</i> (H)	
Bundled Accessories	
Input AC 100 ~ 240V, Output DC 19V 60W	
Norman Virus Control, Norman Personal Firewall, Adobe Acrobat 6.0, CyberLink PowerDVD,	
CyberLink PowerProducer, Fujitsu UpdateNavi™, Fujitsu Hardware Diagnostic Tool	
Norman Virus Control & Norman Personal Firewall	

- Results obtained from Ziff Davis (BusinessWinstone 2001) Battery Mark V1.0.1.
- Actual battery life will vary based on screen brightness, sound volume settings, running applications, connected peripherals, power management settings, battery conditioning, and other customer preferences. DVD or hard disk drive usage may also have a significant impact on battery life.
- Dynamic Video Memory Technology (DVMT) dynamically responds to application requirement and efficiently allocates the proper amount of memory (max. 64MB) for optimal graphics and system performance. The memory size available to the Operating System will be less than the total size of installed memory module.
- Maximum 56Kbps performance varies according to your local service providers' services as well as line condition. V.92 performance is dependent on local service providers' services.
- This term does not represent actual data rate of 100/10Mbps and simply indicates compliance with IEEE 802.3 and IEEE 802.3 standards. Actual maximum network data rate depends on network configurations, cable conditions as well as connected devices.
- This term does not represent actual data rate of 4Mbps and simply indicates compliance with IrDA standard specification 1.1. Actual maximum data rate depends on local configurations and connected devices.

It is natural for all thin-film transistor (TFT) liquid crystal displays (LCD) to show a small number of missing or discoloured dots. These are commonly known as non-conforming pixels. This is a technology limitation of TFT LCD and does not represent a defect. Fujitsu warranty does not cover limitations in technology such as non-conforming pixels.

Specifications reflected above are engineering and hardware specifications. They do not represent actual usage or operating dimensions, sizes, performance and weights as these are dependent on

factors such as operating temperature, type of operating system and applications used, connected devices and accessories as well as hardware configurations of the notebook.





All rights to the mentioned trademarks reside with their respective owners. Fujitsu endeavours to ensure that the information in this documentation is correct and fairly stated, but does not accept liability for any errors or omissions. The development of Fuiltsu products and services is continuous and published information may not be up to date. It is important to check the current position with Fujitsu. The document is not part of the contract or licence save in so far as may be expressly agreed.

Dealer:

SINGAPORE: Fuiitsu PC Asia Pacific Pte Ltd Tel: (65) 6776 0688 Fax: (65) 6776 0788 MALAYSIA:

Fujitsu PC Asia Pacific Pte Ltd Tel: (60-3) 2093 3997 Fax: (60-3) 2093 4245

HONG KONG: Fujitsu PC Asia Pacific Ltd Tel: (852) 3101 8133 Fax: (852) 3101 0633

Fujitsu Systems Business (Thailand) Ltd

PC Division Tel: (66-2) 263 7888 Fax: (66-2) 263 7880 www.fujitsu-pcap.in.th

AUSTRALIA: Fujitsu PC Australia Toll Free: 1800 288 283 Tel: (61-2) 9004 7455

Fax: (61-2) 9004 7720 www.lifebook.com.au

Fujitsu PC China Division Tel: (86-21) 3310 0808

Fax: (86-21) 3310 0606 www.pc-cn.fujitsu.com

Fujitsu Philippines Inc. Tel: (63-2) 812 4001

Fax: (63-2) 817 7576

Fujitsu Taiwan Ltd

PHILIPPINES:

Tel: (886-2) 2311 2255 Fax: (886-2) 2311 2277

VIETNAM: Fujitsu Vietnam Ltd Tel: (84-4) 831 3895~7

Fax: (84-4) 831 3898 INDONESIA: PT Fujitsu Systems

(Indonesia) Tel: (62-21) 344 2601 Fax: (62-21) 344 2593

Note: For countries not listed above, please contact our Singapore office.

