■ General Specifications

Description	Specifications	ScanSnap iX500		
Scanner type		ADF (Automatic Document Feeder), Duplex scanning		
Scanning modes		Color, grayscale, monochrome, automatic (color / grayscale / monochrome *3 detection)		
Image sensor		Color CIS x 2 (front x 1, back x 1)		
Light source		3 Color LED (Red / Green / Blue)		
Auto mode *2		Simplex / Duplex: 25 ppm		
	Normal mode	Color / Grayscale: 150 dpi, Monochrome: 300 dpi, Simplex / Duplex: 25 ppm		
Scanning speed	Better mode	Color / Grayscale: 200 dpi, Monochrome: 400 dpi, Simplex / Duplex: 25 ppm		
(A4 portrait)	Best mode	Color / Grayscale: 300 dpi, Monochrome: 600 dp Simplex / Duplex: 25 ppm		
	Excellent mode *3	Color / Grayscale: 600 dpi, Monochrome: 1,200 dpi, Simplex / Duplex: 7 ppm		
Document	Normal mode without Carrier Sheet	A4, A5, A6, B5, B6, Business card, Post card, Letter, Legal and Custom sizes (Max: 216 x 360 mm (8.5 x 14.17 in.), Min: 50.8 x 50.8 mm (2 x 2 in.))*3/ Automatically recognizes document size		
size	Normal mode with Carrier Sheet *3	Use of a Carrier Sheet permits the scanning of AS B4, 11 x 17 in. and photographs as well as the document sizes that are listed above		
	Long paper scanning *3 *4	863 mm (34 in.)		
Paper weight (Thickness)		●40 to 209 g/m² (11 to 56 lb) ●A8 size: 127 to 209 g/m² or 34 to 56 lb ●Cards (ISO7810 ID-1 type conforming) can be used. (thickness 0.76 mm or less) Embossed card: useable (Landscape only)		
Paper chute	capacity *5	Maximum 50 sheets (A4, 80 g/m² or 21 lb)		
USB Interfac	ce	USB3.0 (USB2.0 / USB1.1 Supported) *6		
	Observed standards	IEEE802.11b / IEEE802.11g / IEEE802.11n		
	Communication mode	Infrastructure mode		
	Frequency *8	2.412 GHz to 2.462 GHz / 2.412 GHz to 2.472 GHz		
Wi-Fi	Communication distance	Indoors, 50 m (Recommended: indoors, within 25 m) *May vary depending on the surrounding environment and the access point to be connected		
Interface *7	Security	WPA-PSK (TKIPI/AES/AUTO), WPA2-PSK (AES), WPA-PSK, WPA2-PSK (AES/AUTO), WPA (TKIPI/AES/AUTO), WPA2 (AES) WPA2 (AES/AUTO), SharedKey (WEP (64-bit/128-bit)), 802.1X (WEP (64-bit/128-bit)) + 9		
	Easy installation	WPS2.0 supported (button / PIN code)		
Power requi	rement	AC 100 to 240 V, 50 / 60 Hz		
Power	USB connected	Operating mode: 20 W or less, Sleep mode: 1.6 W or less, Auto Standby (Off) mode: 0.4 W		
consumption	Wi-Fi connected	Operating mode: 20 W or less, Sleep mode: 2.5 W or less, Auto Standby (Off) mode: 0.4 W		
Operation environment		Temperature: 5 to 35 °C (41 to 95 °F) Relative humidity: 20 to 80 % (Non-condensing)		
Dimensions (W x D x H)*10		292 x 159 x 168 mm (11.5 x 6.2 x 6.6 in.)		
Device weight		3.0 kg (6.62 lb)		
Environmental compliance		ENERGY STAR® / RoHS		
Multifeed detection		Supported (Standard) ultrasonic multifeed detection sensor		
Driver		Specific driver ●Windows®: Does not support TWAIN / ISIS™ ●Mac OS: Does not support TWAIN		

*1 Scanning speeds may vary due to the system environment used. *2 Documents measuring approximately 148 mm in length or less are scanned in "Best mode", while other documents are scanned in "Better mode". *3 Only computer connection *4 ScanSnap iX500 is capable of scanning documents Better mode: ★3 Unly computer connection ★4 Scanshap M30U is capable or scanning of countents that exceed A4 size in length. It supports the scanning of longer documents in all modes, except for "Excellent mode": ★5 Maximum capacity varies, depending upon paper weight. ★6 Some computers do not recognize the Scanshap when it is connected to a USB 3.0 port. In this case, please use a USB 2.0 port. ★7 Mobile devices that can be connected include iPad / iPhone / iPod touch and Android™ devices. Refer to ScanShap website for details. ★8 Values depends on country. ★9 Please update the ScanShap Manager to the latest version for configuring IEEE802.1X authentication. Refer to ScanSnap website for further information. ★10 Excluding the stacker and other external attachments.

Description	Part number	Remarks		
Description	1 di titaliboi	11011110		
ScanSnap Carrier Sheets	PA03360-0013	5 Carrier Sheets Intended for ScanSnap iX500, S1500, S1500M, S1100, S510, S510M		
ScanSnap Bag	PA03951-0651	Intended for ScanSnap iX500, S1500, S1500M, S510, S510M and included items		

*1 Although ScanSnap Carrier Sheets have a listed lifespan of 500 scans, the lifespan may vary with usage. ScanSnap Carrier sheets are intended to scan paper documents with weights of 127 g/m² or less. They also support the scanning of folded documents that are as large as 216 x 297 mm.

We recommend the use of our genuine products for the consumables. Failures, troubles, and damage of this product resulting from the use of consumables other than our genuine products are subject to repair fees even

■ Consumables within the warranty period.					
Description	Part number	Remarks			
Roller Set	PA03656-0001	Lifetime: Every 200,000 sheets or one year. (For ScanSnap iX500 only)			
Cleaner F1	PA03950-0352	100 ml bottle For use on the Brake roller and Pick roller			
Cleaning Wipe	PA03950-0419	1 pack (24 packets) For use on the Brake roller and Pick roller			

* These recommended lifetimes are for 80 g/m² (21 lb) A4 sized documents. Therefore, appropriate

Windows®

Compatible	Compatible operating systems		Windows® 8.1 / 8 (32-bit / 64-bit) *1	Windows® 7 (32-bit / 64-bit)	(20 hit / C/L hit)	Windows® XP (32-bit) SP3 or later	
	ScanSnap Manager	Supported	Supported	Supported	Supported	Supported	
	ScanSnap Organizer	Supported	Supported	Supported	Supported	Supported	
	ScanSnap Receipt *3	Supported	Supported	Supported *4	Supported	Not supported	
Driver / Applications	CardMinder	Supported	Supported	Supported	Supported	Supported	
*2	ABBYY FineReader for ScanSnap™	Supported	Supported	Supported	Supported	Supported	
	Scan to Microsoft® SharePoint®	Supported	Supported	Supported	Supported	Supported	
	Nuance® Power PDF Standard	Supported	Supported	Supported	Not Supported	Not Supported	
	CPU*6	Intel® Core™ i5 2.5 GHz or higher					
	Memory capacity *6	4 GB or more					
Hardware requirements	Display		r higher	800 x 600 pixels or higher			
*5	Disk capacity *7	5 GB free hard disc space for installation					
	DVD-ROM drive	Required for installation *8					
	USB port *6 *9	USB3.0*10 / USB2.0 / USB1.1					

USB port ★ 8 ● USB 3.0 ★ 10 V USB 1.1 W USB port ★ 8 ● USB 3.0 ★ 10 V USB 1.1 V USB 1.1 W USB port ★ 2 Please refer to the ScanSnap website for latest support information. ★ 3 Available via ScanSnap Online Update. ★ 4 Required Service Pack1. ★ 5 The ScanSnap device may not work if the connected computer does not meet these requirements. ★ 6 Scanning speeds may drop if recommended CPU, memory capacity and USB 1.1 requirements are not met. ★ 7 Microsoft .NET Frmework 3.5 SP1 will be installed (requires 500 MB of disk space) together with ScanSnap Manager, ScanSnap Organizer or CardMinder for systems that do not have .NET Framework 3.5 SP1 installed. When using "Scan to Google Drive" with ScanSnap Manager/ScanSnap Organizer, users also need to install either .NET Framework 4 or in-place updates of .NET Framework 4. ★ 8 If you have no DVD-ROM drive, please visit the following website: http://scansnap.fujitsu.com/g-support/en/ ★ 9 ScanSnap operates on both USB 2.0 and USB 3.0 without any difference in performance. ★ 10 Some computers do not recognize the ScanSnap when it is connected to a USB 3.0 port. In this case, please use a USB 2.0 port. ★ 9 System requirements may change depending on the duration of support and the support a USB 2.0 port. *System requirements may change depending on the duration of support and the support policy of the companies that make the software listed in the table above.

Mac OS

- Ivido ot								
Compatible operating systems		OS X v10.11	OS X v10.10	OS X v10.9	OS X v10.8	Mac OS X v10.7	Mac OS X v10.6	
	ScanSnap Manager	Supported	Supported	Supported	Supported	Supported	Supported	
	ScanSnap Organizer	Supported	Supported	Supported	Supported	Supported	Not Supported	
Driver /	ScanSnap Receipt *6	Supported	Supported	Supported	Supported	Supported	Not Supported	
Applications	CardMinder	Supported	Supported	Supported	Supported	Supported	Supported	
	ABBYY FineReader for ScanSnap™	Supported	Supported	Supported	Supported	Supported	Supported	
	Nuance® PDF Converter for Mac	*7	Supported	Supported	Supported	Supported	Not Supported	
	CPU*9	Intel® Core™ i5 2.5 GHz or higher)						
	Memory capacity *9	4 GB or more						
Hardware	Display	1,024 x 768 pixels or higher						
requirements	Disk capacity	2.5 GB free hard disc space for installation						
*8	DVD-ROM drive	Required for installation*10						
	USB port *9 *11	USB3.0 *12 / USB2.0 / USB1.1						

information. *8 The ScanSnap device may not work if the connected computer does not meet these requirements. *9 Scanning speeds may drop if recommended CPU, memory capacity and USB 1.1 requirements are not met. *10 if you have no DVD-ROM drive, please visit the following website: http://scansnap.fujitsu.com/g-support/en/ *11 ScanSnap operates on both USB 2.0 and USB 3.0 without

■ Software Windows®		Mac OS		
Driver *1 *2	ScanSnap Manager	ScanSnap Manager		
	ScanSnap Organizer	ScanSnap Organizer		
	ScanSnap Receipt	ScanSnap Receipt		
Applications	CardMinder	CardMinder		
Applications	ABBYY FineReader for ScanSnap™	ABBYY FineReader for ScanSnap™		
	Scan to Microsoft® SharePoint®	-		
	Nuance® Power PDF Standard	Nuance® PDF Converter for Mac		

*1 TWAIN or ISIS™ applications cannot be used directly. *2 Image file (JPEG, PDF and searchable PDF) can be generated by "One Touch". The function is operable with ScanSnap Manager (ScanSnap specific driver).

■ ScanSnap ■ AC cable ■ AC adapter ■ USB cable (USB 3.0 supported) ■ Safety Precautions ■ Setup DVD-ROM ■ Nuance® Power PDF Standard / Nuance® PDF Converter for Mac DVD-ROM

This scanner is designed to digitize materials that can be reproduced lawfully, in accordance with applicable copyright regulations and other laws. ScanSnap users are responsible for how they use this scanner. It is imperative that ScanSnap users comply with all applicable local rules and laws, including, without limitation, copyright laws when using this scanner.

Users comply with all applicable local rules and laws, including, without limitation, copyright laws when using this scanner.

*ABBYY and FineReader are trademarks of ABBYY Software, Ltd. which may be registered in some juriscitions. ABBYY™ FineReader™ Engine (ABBYY, OCR by ABBYY) *Evenote is a registered trademark or trademarks of Evenote Corporation. **Google, Google Drive and Android are registered trademarks of Koogle, Google Drive and Android are registered trademarks or trademarks



PFU LIMITED, a Fujitsu company, has determined that this product neets the ENERGY STAR® guidelines for energy efficiency. ENERGY STAR® is a registered trademark of the United States.

For more ScanSnap related information, visit our website at : http://scansnap.fujitsu.com/

Specifications are subject to change without notice.

Safety Precautions

Be sure to carefully read all safety precautions prior to using this product and use this device as instructed.

Do not place this device in wet, moist, steamy, dusty or oily areas. Using this product under such conditions may result in electrical shock, fire or damage to this product.

©2016 PFU LIMITED Printed in some country 2016.2 U-109 AMN 50K4



ScanSnap iX500

Simple, Speedy & Compact. From Paper to PDF in one touch!

Features

- ▶ Wi-Fi connectivity to computer and mobile
- ▶ Can scan at high speed with a "GI processor"
- ▶ Can feed paper reliably using "Brake rollers"
- ▶ Ultrasonic sensors for efficient and trouble-free scanning
- ▶ Various functions for making your daily work easier and simpler

- Nuance® Power PDF Standard (Win),
 Nuance® PDF Converter for Mac (Mac)
- ► CardMinder (Win / Mac)



shaping tomorrow with you

*1 Recommended: v10.9.5 or later *2 Recommended: v10.8.5 or later *3 Recommended: v10.7.5 or later *4 Recommended: v10.6.8 *5 Please refer to the ScanSnap website for latest support information. *6 Available via ScanSnap Online Update. *7 Please refer to the ScanSnap website for latest support

to a USB 3.0 port. In	ormance. *12 Some computers do not re- this case, please use a USB 2.0 port. * Sys rt and the support policy of the companies tha	stem requirements may change depending or
■ Software	Windows®	Mac OS
Driver *1 *2	ScanSnap Manager	ScanSnap Manager
	ScanSnap Organizer	ScanSnap Organizer
	ScanSnap Receipt	ScanSnap Receipt

Delivering "total support" from digitization to application. The amazingly versatile, ScanSnap ix500!

Scan large volumes of documents

The iX500 is ideal for reducing paper storage space, while also scanning reliably for fast and efficient data management.

To perfect PDF files in One Touch

Simply push the scan button and let the array of automatic image enhancing functions digitize your documents to high quality PDF image files every time.

Speedy document digitization

Digitize up to 50 double-sided sheets at a speedy 25 pages per minute.

Smaller than an A4 size laptop

The iX500 is compact enough to be placed just about anywhere.

Scan anything from business cards to A3 size documents

Using Carrier Sheets, the iX500 can digitize documents up to A3 size, as well as magazine and newspaper clippings, photographs and much more. Scan Carrier Sheets in succession or mixed in with other papers.



Wi-Fi connectivity to computer and mobile

You can connect iX500 to computer via Wi-Fi. * Connect to the computer via Wi-Fi while enjoying all the same functions as USB connection, including various automation functions, applications and cloud service linkage. As you do not need to connect using a USB cable, you can place iX500 anywhere.

- *Update ScanSnap Manager to the latest version is necessary in order to use this function. Follow the instructions when prompted by "ScanSnap Online Update" which will be notified automatically.
- *Function, performance and operability are the same as USB connection when connected via Wi-Fi. However, scanning speed may be reduced due to the network environment used.
- *Wi-Fi access point/router is necessary in order to connect to Wi-Fi. *Only one computer can be registered for Wi-Fi connection.









You can scan directly from and save scan data to smartphones or tablets in PDF format (JPEG format also is available) via Wi-Fi.











New "GI" processor architecture



The newly developed dual-core CPU "GI" processor achieves quality image processing at the scanner while supporting the newest interfaces. You can digitize documents carefree with smartphones, tablets, or computers.


- Image processing functions* (Automatic Functions*, scanned image outputting)
- Supports Wi-Fi (WPS (Wi-Fi Protected Setup) wireless LAN (IEEE802.11b / g / n))
- ■Supports USB3.0
- *Scanner's functions are different when connecting to a computer and a mobile device. Refer to ScanSnap website for details.

Document separation by Brake rollers

Inheriting the superior paper feeding technology of our professional-use scanners, iX500 separates documents using "Brake

rollers". Stable paper feeding minimizes troubles such as multifeeding and paper jams.







Ultrasonic multifeed detection

iX500 uses ultrasonic sensors for efficient and trouble-free scanning.

Ouick Menu saves time

Even first-time ScanSnap user can master the functions by navigating through the Quick Menu. ScanSnap's Quick Menu automatically pops up after scanning to enable you to link the data to an application, quickly and easily. You do not have



to remember any complicated procedures; just simply click the icon on screen.

Ouick Menu: Favorites (Windows®

It can be easily customized to display just your



Creates searchable PDFs faster

PDFs with text information can now be created at practically the same speed as normal PDF files, allowing for immediate use with cloud services and applications.

*Please visit the ScanSnap website for details on which languages and currencies are supported.



Easily links documents to clouds

You can scan nearly effortlessly to Evernote, Google Drive, Salesforce, SugarSync and Dropbox, and then conveniently browse the data from computers, tablets or smartphones anywhere, anytime.

■ScanSnap Folder [Windows®]

Scan to virtually any application or web service that can open, insert or attach a PDF or JPEG file from your Windows computer. In this way, you do not have to save the data in the computer beforehand.



Making ScanSnap Connect Application more convenient

With ScanSnap Sync, whichever device you are on, you can use scanned data from either ScanSnap Organizer or the mobile app ScanSnap Connect Application. ScanSnap Sync automatically synchronizes scanned data between the two. This gives you more flexibility for data management regardless of your location.

*ScanSnap Sync is realized by utilizing a third party cloud service such as Google Drive, OneDrive and Dropbox. For the latest support information of cloud services, please visit the ScanSnap website

Efficiently organizes business card data

Business card organizer software

CardMinder [Windows® / Mac OS]

Scan your collection of business cards into easy to navigate digital business card holders.



Sugar**Sync**

EVERNOTE

Salesforce Chatter

Salesforce CRM

•Import the data from your scanned business cards into Excel, Outlook, Address book (Contacts: OS X v10.8 or later) and other database programs for fast referencing and application.

Receipt software with multi-currency support A few simple steps to digitize and manage the information on your receipts

ScanSnap Receipt allows you to easily scan and extract information from your receipts, and export the data for other accounting software. The sophisticated features within ScanSnap Receipt automatically support various languages and currencies.

*Please visit the ScanSnap website for details on which languages and currencies are supported.