LifeBook N6420

- Brilliant 17-inch wide super clarity SuperFine display excellent for movie viewing
- Support viewing of HD DVD content
- Unique dedicated numeric 10-key and mega storage up to 400GB7
- Enhance personal productivity with TV recording functions for multimedia playback anytime, anywhere
- Health and environment friendliness with RoHS compliance⁶
- Designed for Genuine Windows Vista[™] operating system



	Recommended Configurations	
Platform	Intel® Centrino® Duo Mobile Technology	Intel® Centrino® Duo Mobile Technology
	 Intel® Core™2 Duo Processor T7400 (2.16GHz, 4MB L2 cache, 667MHz FSB) 	- Intel® Core™2 Duo Processor T5600 (1.83GHz, 2MB L2 cache, 667MHz FSE
	- Intel® PRO/Wireless 3945ABG/3945BG network connection	- Intel® PRO/Wireless 3945ABG/3945BG network connection
	- Intel® 945PM Express Chipset	- Intel® 945PM Express Chipset
OS Supported	Genuine Windows Vista™ Ultimate	
	(or Genuine Windows Vista™ Home Premium)	
Display	17-inch SuperFine WXGA+ TFT, 1440 x 900 pixels, 370nits Brightness, 600	0:1 Contrast Ratio, 72% Color Gamut
Built-in Bay Device	HD DVD ROM	Dual Layer DVD Super Multi Writer ⁵
Memory	2GB DDR2 667MHz	1GB DDR2 667MHz
Hard Disk	400GB ⁷ (200GB x 2)	100GB ⁷
Battery	Up to 1.1hrs1 (6-cell Li-lon 4000mAh)	Up to 1.4hrs1 (6-cell Li-lon 4000mAh)
Weight	Approx. 4.8kg	
TTO I GITT	Specifications	
Max. Memory Supported	4GB DDR2 667MHz, Dual Channel	
Hard Disk Drive	SATA-150, S.M.A.R.T support	
Graphics	ATI Mobility™ Radeon® X1600 with 512MB HyperMemory™8, PCI Express	ATI Mobility™ Radeon® X1400 with 256MR HyperMemory™8 PCI Expr
High Definition (HD) Audio	RealTek ALC262 HD audio codec with built-in dual stereo soeakers and subwoofer	
riigii beiiiililoii (Hb) Addio	HD Audio-in: Mic-in	
	HD Audio-out: Headphone-out, SPDIF	
Communication	nD Audio-Out. readprillone-out, S-ruir 56K V92 ² Global Modem MDC1.5, 1000/100/10Mbps ³ Gigabit Ethernet PCI Express x 1 and Intel® PRO/Wireless 3945ABG/3945BG network connection	
	Son Vis2. Global Modern MD L.S., TUDI TOU TOU TOURD SET Glabal Express x + and Intel® PRO/Wireless 3949ABG/3949BG network connection with dual antenna. Separate ON/OFF switch for wireless network connection	
User Interface	with qual antenna, separate UN/OFF switch for wireless network connection Keyboard: 103-key, 19mm key pitch, 3mm key stroke, dedicated numeric 10-keys	
	Reyboard: 103-key, 19mm key pitch, 3mm key stroke, dedicated numeric 10-keys Intelligent Touch Pad with scroll buttons	
	Intelligent rouch Pad with scroll buttons MCE Remote Controller	
Card Slots	MUE Hemote Controller PC Card Type II	
	ExpressCard™/ 34/54 support	
	Secured Digital/ Memory Stick®/ Memory Stick® PRO/ xD	
Connector Interface	USB 2.0 x 5, VGA (external display), RJ45 (LAN), RJ11 (modem), IEEE1394, S-Video out, HDA-in, HDA-out, Power Adapter DC-in	
Built-in TV Tuner	Antenna Signal Input: 75Ω, mini-jack to F-connector/ IEC connector, RG-6U coaxial cable provided	
	Video Input: Composite Video, RCA yellow, S-Video	
	Video Output: 720 x 480 pixel resolution, MPEG2 compression	
	Audio Input: RCA white, RCA red, MPEG2 audio compression	
	TV System Supported: PAL	
Quick Launch Panel	Four Programmable Application Launch Buttons (Internet, Email and two other softwares), TV Button, DVD/CD Button, Visual Optimizer Button,	
	TV Channel Button, Volume Control Button	
Security ⁴	BIOS Lock, Hard Disk Lock, Anti-theft Lock Slot	
Dimensions	403mm (W) x 295mm (D) x 45.5mm-51.3mm (H)	
	Bundled Accessories	
AC Adapter	Input AC 100~240V, Output DC 19V 150W	
MCE Remote Controller Set	Use the remote controller to perform actions on the LifeBook wirelessly e.g. playing DVDs, listening to music, viewing digital photo albums and controller	
	TV functions	
Bundled Software	CyberLink PowerDVD™, CyberLink PowerProducer™, Roxio Easy Media Creator, Adobe Acrobat Reader, Fujitsu UpdateNavi ⁹ ,	
	Fujitsu Hardware Diagnostic Tool, Fujitsu Display Manager, Sun Microsystems Java Runtime	
Software on CD	1 year Full Licensed Norman Virus Control with Sandbox Technology and Norman Personal Firewall, Acronis True Image	
	Optional Accessories	
Floppy Disk Drive	External USB 1.44MB FDD	
Mouse	USB Optical Scroll Mouse	
	p	

The above information shows the general technical specifications of the product and does not represent actual configuration. For specific configurations and their availability, please check with your local distributors.

- Passults obtained from BAPCO MobileMark2005 (Productivity Workload) performed on systems with maximum battery life settings. Actual battery life will vary based on screen brightness, sound volume settings, running applications, connected peripherals, power management settings, battery conditioning, and other customer preferences. Built-in bay device or hard drive usage may also have a significant impact on battery life.

 2 Maximum Schöpps performance varies according to your local service providers' services as well as line condition. V32 periodical providers are local service providers' services.

 3 This term does not represent actual data rate of 1000/100/10Mtps and simply indicates compliance with IEEE 802.3µ EEE 802.3µ and IEEE 802.3a standards. Actual maximum data rate depends on network configurations, cable conditions as well as

- connected devices a supervisor/user password to access BIOS setup. BIOS settings can be configured to prompt for password at supervisor/user password to access BIOS setup. BIOS settings can be configured to prompt for password at post-priest boot up sequences. Access to BIOS setup is needed to configure that Disk Lock requires an access key to retrieve data on the hard disk. This is a Data Confidentiality security feature. Anti-that Lock Sol allows the use of a lock to physically secure the LifeBook.

 NOTE: Loss of password equires the LifeBook in the returned to Japan factory for system refresh. Cost of shipment and lost data will be borne by the customer. Loss of the Hard Disk Lock password means the HDD content cannot be retrieved. It is the customer's responsibility to ensure the safe keeping of the password for retrieval of data from the locked HDD.

 Supports DVD multi formats such as DVD-RAM, DL DVD-R, DVD-RVD, DVD-RVD,

- i is a Fujitsu Proprietary application that updates LifeBook drivers by connecting automatically to Fujitsu's server. This will help update your LifeBook with the latest software drivers and utilities to ensure compatibility between hardware and software, smooth operation anytime, anywhere.

"PCI Express" and the PCI Express design marks are registered trademarks and/or service marks of PCI-SIG.

Dolby and the double-D symbol are registered trademarks of Dolby Laboratories.

It is natural for all thin-film transistor (TFT) liquid crystal displays (LCD) to show a small number of missing or discolored dots. These are commonly known as non-conforming pixels. This is a technology limitation of TFT LCD and does not represent a defect. Fujitsu warranty does not cover limitations in technology such as non-conforming pixels.

Specifications reflected above are engineering and hardware specifications. They do not represent actual usage or operating dimensions, sizes, performances and weights as these are dependent on factors such as operating temperature, type of operating system application used, connected devices and accessories as well as hardware configurations of the notebook. Please othet the compatibility of 3rd party accessories before purchase. Ambient temperature: 5° to 35°C / 41 to 95°F (operating), -15° to 60°C / 5 to 10°C / 5 to 10°C / 60°C / 60









AUSTRALIA & NEW ZEALAND: Fuiitsu PC Australia

Toll Free: 1800 288 283 Tel: (61-2) 8877 9500 Fax : (61-2) 9889 3360 www.lifebook.com.au

CHINA: Fuiitsu PC China

Tel: (86-21) 3310 0808 Fax: (86-21) 3310 0606 cn.fujitsu.com/pc

HONG KONG: Fujitsu PC Asia Pacific Ltd Tel: (852) 3101 8133 Fax: (852) 3101 0633

INDIA: Fujitsu India Limited Tel: (91-11) 2370 6070

Fax: (91-11) 2370 6079 INDONESIA:

Fuiitsu Indonesia Tel: (62-21) 570 9330 Fax: (62-21) 573 5150

MALAYSIA: Fujitsu PC Asia Pacific Pte Ltd Tel: (60-3) 2093 3997

Fax: (60-3) 2093 4245

PHILIPPINES: Fujitsu Philippines Inc. Tel: (63-2) 812 4001 Fax: (63-2) 817 7576

SINGAPORE: Fujitsu PC Asia Pacific Pte Ltd

Tel: (65) 6776 0688 Fax: (65) 6776 0788

TAIWAN-Fujitsu Taiwan Ltd

Tel: (886-2) 2311 2255 Fax: (886-2) 2311 2277

Fujitsu Systems Business (Thailand) Ltd PC Division

Tel: (66-2) 263 7888 Fax: (66-2) 263 7880

VIFTNAM: Fuiitsu Vietnam Ltd

Tel: (84-4) 831 3895 Fax: (84-4) 831 3898

Note: For countries not listed above, please contact our Singapore office.









All rights to the mentioned trademarks reside with their respective owners. Fujitsu endeavours to ensure that the information in this documentation is correct and fairly stated, but does not accept liability for any errors or omissions. The development of errors or omissions. The development of Flyjitsu products and services is continuous and published information may not be up to date. It is important to check the current position with Fujitsu. The document is not part of the contract or licence save in so far as may be expressly agreed.